MICROCOPY RESOLUTION TEST CHART

NATIONAL BUREAU OF STANDARDS-1963

PARAMETER ESTIMATION FOR THE BLIND
RESTORATION OF BLURRED IMAGERY

THESIS

Murat Cincioglu
Lieutenant, Turkish AF

AFIT/GE/ENG/86S-1

DTIC
ELECTE
MAR 1 6 1987
S E D

DEPARTMENT OF THE AIR FORCE
AIR UNIVERSITY
AIR FORCE INSTITUTE OF TECHNOLOGY

Wright-Patterson Air Force Base, Ohio

87 3 12 084

PARAMETER ESTIMATION FOR THE BLIND
RESTORATION OF BLURRED IMAGERY

THESIS

Murat Cincioglu
Lieutenant, Turkish AF

AFIT/GE/ENG/86S-1

September 1986

PARAMETER ESTIMATION FOR THE BLIND

RESTORATION OF BLURRED IMAGERY

THESIS

Presented to the Faculty of the School of Engineering

of the Air Force Institute of Technology

Air University

in Parital Fulfillment for the

Master of Science in Electrical Engineering

Murat Cincioglu

Lieutenant, Turkish AF

September 1986

Acknowledgements

I wish to express my deepest gratitude and appreciation
to my academic and thesis advisor, Major David A. King who kindly
offered invaluable help and guidance throughout my course of study
in the AFIT and preparation of this thesis.

I would also like to thank the professors and officers
of the United States Air Force Institute of Technology for
the consistent professionalism and the friendship which they
have shown to me during my course of study in the United States
of America.

Table of Contents

List of Figures

List of Tables

List of Symbols

$f(x,y)$	Original (undegraded) image.
$F(u,v)$	Discrete Fourier transform of the original image.
$\hat{f}(x,y)$	Estimated (restored) image.
$\hat{F}(u,v)$	Discrete Fourier transform of the restored image.
$h_d(x,y)$	Point-spread-function (PSF) of the degrading system.
$H_d(u,v)$	Optical Transfer Function (OTF) of the degrading system.
$h_r(x,y)$	Point spread function of the restoration system.
$H_r(u,v)$	Optical Transfer Function of the restoration system.
$g(x,y)$	Degraded image.
$G(u,v)$	Discrete Fourier Transform of the degraded image.
$n(x,y)$	Noise.
$N(u,v)$	Discrete Fourier transform of $n(x,y)$.

Abstract

Methods to estimate the optical transfer function (OTF) of the degradation and the noise-to-signal ratio in a degraded image are presented which use no prior information about the degradation and the noise. Two types of degradations are considered: uniform linear camera motion and out-of-focus camera with circular aperture. The OTF of the out-of-focus camera is estimated by inspection of the spectra of the degraded image and from average over the spectra of subsections of the degraded image. A line estimation method is described to estimate the degrading OTF of the linear camera motion in one direction. An additional method called the "logarithmic estimate" is also developed. Frequency and space domain estimation methods are developed for the noise-to-signal ratio for the case of additive gaussian noise. Inverse, Wiener, and power spectrum equalization filters based on these estimates are implemented on a digital computer to restore a variety of degraded images and examples of blind restoration of these degraded images are presented.

PARAMETER ESTIMATION FOR THE
BLIND RESTORATION OF
BLURRED IMAGERY

I. Introduction

Background

One of the major applications of digital image processing is image restoration. Image restoration is an estimation process that attempts to recover an original (ideal) image from a degraded image. These degradations are incurred while the image was being acquired and may include the blurring introduced by optical systems, atmospheric turbulence, camera/object motion, as well as distortion and noise due to electronic and photometric sources.

The overall performance of image restoration process greatly benefit from modelling of the transfer function of the degradation and characterization of the noise in the degraded image. If a prior knowledge of the image and the imaging system is available, it can be used to increase the performance of the restoration system. If little or nothing is known about the image, one can attempt to model and characterize the sources of degradation (blurring and noise) and subsequently remove or reduce their effects. When a prior knowledge about the image isnot available, information about the degradation must be extracted from the observed (degraded) image. This task is called blind image restoration.

1

The Foreign Technology Division (FTD) at Wright-Patterson AFB
has needed a blind image restoration method to deblur photographs taken
under controlled conditions. Most of the restoration filters such as
Wiener filter, inverse filter, power spectrum equalization filter
require the degrading optical transfer function and/or the noise-to-
signal ratio as their parameters. In order to restore a degraded image,
one must know the degrading OTF (optical transfer function) and the NSR
(noise-to-signal power ratio). Since no prior information about these
two parameters is available, one has to estimate them from the degraded
image itself. Once the degrading OTF and the NSR are estimated, any of
the restoration filters (methods) can be employed to restore the degraded
image. Therefore, the problem of the blind restoration reduces to
estimation of the degrading OTF and the NSR.

Statement of the Problem

The problem that is addressed in this thesis may be stated as
follows:

> Given a degraded image with no information
> available concerning the degradation function
> and the noise, develop methods to estimate the
> degrading OTF and the NSR and use them to
> restore the degraded image.

Scope

This thesis is primarily concerned with the estimation of the
degrading OTF and the NSR. Inverse filter, Wiener filter, and power

2

spectrum equalization filter are presented as restoration methods. Other restoration techniques and the investigation of their performance with the estimated degrading OTF and the NSR are considered out of the scope of this thesis. Two specific cases of the degradation will be considered: uniform camera motion and out-of-focus lens system with circular aperture. Restoration for other forms of degradations, such as blurring due to atmospheric turbulence, camera vibration, geometric distortion, and system nonlinearities will not be addressed. The primary objectives of this effort can be stated as:

1. Develop a method to estimate the degrading OTF.

2. Develop a method to estimate the noise-to-signal power ratio.

3. Implement the results by a general purpose restoration filter on a digital computer.

Assumptions

The imaging system and the degradation system will be assumed as linear space-invariant systems. We will assume that the original image and the noise are spatial stochastic random processes and that they are spatially stationary and statistically independent. The noise process is assumed to be additive gaussian process with mean value of zero.

Approach

Presentation of this research will proceed in Chapter 2 with a discussion of general theory concerning the linear space invariant system, image formation system, the degrading optical transfer functions, noise process and image restoration methods. This is followed in Chapter 3 with discussions of the methods to estimate the degrading OTF for the cases of uniform linear camera motion blur and out-of-focus camera blur and the noise-to-signal power ratio. In Chapter 4, we discuss the implementation of these estimation methods and their performance in actual degraded images. In Chapter 5, we summarize our findings and recommend topics for continuing research.

Materials and Equipment

All thesis research was accomplished in the Signal Processing Laboratory at AFIT utilizing the Data General Eclipse S/250 and Nova computers and the Octek Image Analyzer. The digital images used in this research were 256x256 monochrome images with four bits per pixel. The images were acquired by a variety of techniques, including optical scanning/digitization of photographic film, frame grabbing from a vidicon, and computer generation. Programming was accomplished using FORTRAN IV and FORTRAN 5. Existing software was used for image acquisition and display, two dimensional Fourier transformation and inversion, and image file input/output.

II. Image Restoration Theory

Linear Space Invariant Systems

We can think of a system as a mapping of a set of input
functions into a set of output functions. For the case of
electrical networks, the input and output functions are real
functions (voltages or currents) of a one dimensional indepen-
dent variable (time): for the case of imaging systems, the
inputs and outputs can be real-valued functions (intensity) or
complex-valued functions of a two-dimensional independent
variable (space).

A single-input single-output two dimensional system can be
represented by a mathematical operator "P", which operates on an
input function $f(x,y)$ to produce an output function;
$g(x,y)$, i.e.,

$$g(x,y) = P \{f(x,y)\} \tag{1}$$

The system is linear, if the superposition property is
obeyed for all input functions $f_1(x,y)$, and $f_2(x,y)$, and all com-
plex constants "a" and "b";

$$P\{af_1(x,y) + bf_2(x,y)\} = aP\{f_1(x,y)\} + bP\{f_2(x,y)\} \tag{2}$$

The great importance of linearity is the ability to express the
response to a complicated input by first decomposing this input
into a linear combination of elementary functions and then taking

5

the same combination of these elementary responses. Such a decomposition may be obtained by the sifting property of the delta function which states that

$$f(x,y) \ = \ \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} f(\gamma,\beta) \ \delta(x-\gamma, \ y-\beta) \ d\gamma \ d\beta \qquad (3)$$

$f(\gamma,\beta)$ is considered as weighting factor applied to $\delta(x-\gamma, \ y-\beta)$. Combining Equations (1) and (3), we obtain

$$g(x,y) \ = \ P\{ \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} f(\gamma,\beta) \ \delta(x-\gamma, \ y-\beta) \ d\gamma \ d\beta\} \qquad (4)$$

If the system is a linear system, then applying linearity property to Equation (4), we can obtain

$$g(x,y) \ = \ \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} f(\gamma,\beta) \ P\{\delta(x-\gamma, \ y-\beta)\} \ d\gamma \ d\beta \qquad (5)$$

Now, let the $h(x,y; \ \gamma,\beta)$ be the response of the system at point (x,y) of the output space to a delta function input at coordinates (γ,β) of the input space, thus,

$$h(x,y; \ \gamma,\beta) \ = \ P\{\delta(x-\gamma, \ y-\beta)\} \qquad (6)$$

This function is called the point spread function (PSF) of the system. The system input and output now can be related to each other by the following equation

$$g(x,y) \ = \ \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} f(\gamma,\beta) \ h(x,y; \ \gamma,\beta) \ d\gamma \ d\beta \qquad (7)$$

This expression is known as the superposition integral.

A system is said to be space-invariant (shift-invariant or isoplanatic), if the behavior of the system is not a function of the independent variable (space). Thus if the linear system is also space-invariant, then the impulse response of the system will be

$$h(x,y; \gamma,\beta) = h(x-\gamma, y-\beta) \tag{8}$$

and, we can express the input output relationship for a linear space invariant system as follows

$$g(x,y) = \int\limits_{-\infty}^{\infty} \int\limits_{-\infty}^{\infty} f(\gamma,\beta) \, h(x-\gamma, y-\beta) \, d\gamma d\beta \tag{9}$$

Equation (9) states that the output of a two-dimensional linear, shift-invariant system is the two-dimensional convolution of the input function with the point spread function of the system.

Imaging System

An imaging system consisting of lenses, prisms, mirrors and so on can be considered as a black box which provides a transformation or mapping of input light distribution or input energy radiated from the object to some output spatial light distribution or radiant energy.

7

Figure 1 Generalized Imaging Systems (Ref. 1)

Such an imaging system can be characterized by an entrance pupil,

representing a finite aperture through which radiant energy (light)

passes through to reach imaging elements, and an exit pupil

representing again a finite aperture which radiant energy must pass

as it leaves the imaging elements to reach the image plane.

In Figure 1, a point source in the object plane at coordinates

(x, y) of intensity $f(x,y)$ radiates energy toward the imaging system

entrance pupil. The energy coming from the system exist pupil

produces an intensity distribution $g(x_i,y_i)$ in the image plane. It is

assumed that passage of the energy between the entrance and exit pupil

can be described by geometrical optics.

In most image formation systems the energy radiation emitted

by an object arises from transmitted or reflected light from an

incoherent light source. The energy radiation can often be regarded

8

as quasimonochromatic in the sense that the spectral bandwith of the energy radiation detected at the image plane is small with respect to the center of the radiation. Under these assumptions, the imaging system of Figure 1 will respond as a linear system in terms of the intensity of its input and output fields (Ref. 1). The relationship between the image intensity and the object intensity for the imaging system can then be expressed by the superposition integral; i.e.,

$$g(x_i, y_i) = \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} h(x_i, y_i; x, y) \, f(x, y) \, dx \, dy \tag{10}$$

where $h(x_i y_i; x, y)$ is the image intensity response of the system at point (x_i, y_i) of the image plane to a point source of light at coordinates (x, y) of the object plane. If the intensity impulse response is space invariant, the input output relationship can be expressed by convolution equation

$$g(x_i, y_i) = \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} h(x_i - x, \ y_i - y) \, f(x, y) \, dx \, dy \tag{11}$$

If we take Fourier transform of the both sides of Eq. (11)

$$G(u, v) = H(u, v) \, F(u, v) \tag{12}$$

where $H(u, v)$ is called the optical transfer function (OTF), and the magnitude $|H(u, v)|$ of the OTF is known as the modulation transfer function of the system (Ref. 1).

Image Restoration System Model

Figure 2   Image Restoration System

An image restoration system can be modeled as in Figure 2. The original (ideal) image $f(x,y)$ is degraded by the operation $h_d(x,y)$ and a noise $n(x,y)$ added to form the degraded image $g(x,y)$. This is convolved with the restoration filter point spread function $h_d(x,y)$ to produce the restored image $\hat{f}(x,y)$.

The degradation system models the source of degradation in the image.   There are many sources of degradation. Some types do not involve blur, while effecting only the gray levels of the individual picture points.   Other types which do involve blur are called spatial degradations.   Such degradations can be introduced by atmospheric turbulence, aberrations of the camera and the object.   We will only be concerned with the spatial degradations which are due to uniform linear camera motion and out-of-focus lens system.   The degradation system and restoration system can be considered as the imaging system of Figure 1. Therefore, these systems will respond as a linear system in terms of the

10

intensity of their input and output fields. If the degradation

system models an out-of-focus camera, then this system will introduce

a defocusing at the output. A shift in the position of its input will

not effect the defocusing introduced by the system. The only effect

caused by a shift in the position of its input will be an equal shift

in the position of its output, i.e., it will introduce the same

amount of defocusing. This may be an idealization when applied to

physical systems. But, we will assume that the degradation and

restoration systems are linear space-invariant systems. Therefore,

degraded and restored images can be expressed as

$$g(x,y) = \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} h_d(x-\gamma,\ y-\beta)\ f(\gamma,\beta)\ d\gamma d\beta + n(x,y) \tag{13}$$

and

$$\hat{f}(x,y) = \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} h_r(x-\gamma,\ y-\beta)\ g(\gamma,\beta)\ d\gamma d\beta \tag{14}$$

By taking the Fourier transforms of both sides of these equations,
we obtain

$$G(u,v) = H_d(u,v)\ F(u,v) + N(u,v) \tag{15}$$

$$\hat{F}(u,v) = H_r(u,v)\ G(u,v) \tag{16}$$

where $G(u,v)$, $F(u,v)$, $\hat{F}(u,v)$, $H_d(u,v)$, $H_r(u,v)$, $N(u,v)$ are the Fourier

transforms of $g(x,y)$, $f(x,y)$, $\hat{f}(x,y)$, $h_d(x,y)$, $h_r(x,y)$, $n(x,y)$

respectively. The function $H_d(u,v)$ is the transfer function of the

11

system that transforms ideal (original) image, $f(x,y)$, into the degraded image $g(x,y)$. The function $H_r(u,v)$ is the transfer function of the restoration system which makes as good an estimate as possible of the original image $f(x,y)$.

In order to determine such a transfer function, $H_r(u,v)$ we need some form of information about the degrading transfer function. In some cases, the form of the degradation can be used for determining the $H_d(u,v)$. Therefore, we will, first, restrict our attention to some specific forms of degradations and their transfer functions. We will later consider the case of blind restoration where we assume no prior knowledge of the degradation and must estimate the degrading transfer function from the degraded image.

OTF of Some Specific Degradations

Some common forms of degradations can be characterized by specific transfer functions. If we know the degradation form, we can obtain the parameters of that degrading transfer function from the degraded image, and use these parameters to obtain the same form of degrading transfer function. We will examine the degrading transfer functions which are produced by linear camera motion, and out-of-focus camera.

OTF of Linear Camera Motion

A relative motion between camera and object produces a blur in the image in the direction of the motion. We will assume that the image is invariant in time except for the motion. If a point K_i is

12

selected in the image plane, the instantaneous image intensity

at this point will be denoted by $g(K_i, t)$. The total exposure at any

point of the recorded image can be described by the integrated

image intensity at this position (Ref. 2).

$$g(K_i) = \int_0^T g(K_i, t) \, dt \tag{17}$$

where T is the total exposure time. The medium that actually

performs the integration could be photographic film or the

phosphor in the camera sensor. Assuming that energy is conserved

by the imaging system at any instant during the exposure, the energy

radiated and collected by a small area in the object plane around

the object point K_o is described by

$$g(x_i, y_i) \, dx_i \, dy_i = f(x_o, y_o) \, dx_o \, dy_o \tag{18}$$

at a fixed time t. And, we can say that

$$g(K_i, t) = f(K_o, t) \tag{19}$$

and time integral can be written as

$$g(K_i) = \int_0^T f(K_o, t) \, dt \tag{20}$$

This relation shows that a recorded image point $g(K_i)$ over the

exposure time T will be obtained by performing a summation over all

object points that are imaged onto the image point. If there were

no motion of either object or camera, this relationship would become

13

$$g(K_i) = f(K_o, t) \ T \qquad (21)$$

Since we have assumed that object is a two-dimensional entity and the image is time invariant except for the motion, we can rewrite the recorded image intensity as

$$g(x_i, y_i) = \int_0^T f[x_o(t), y_o(t)] \ dt \qquad (22)$$

Given a description of the object motion R(t), we can convert this time integral into a positional integral over an equivalent stationary object. Let the path of the object motion be described in two-dimensional object plane as a parametric function of the time

$$R(t) = [x_o(t), y_o(t)] \qquad (23)$$

The elemental length ds of the path R(t) is given by

$$ds = \left[\left(\frac{dx_o(t)}{dt} \right)^2 + \left(\frac{dy_o(t)}{dt} \right)^2 \right]^{\frac{1}{2}} dt \qquad (24)$$

The time integral in equation (22) can then be changed into the line integral of the form

$$g(x_i, y_i) = \int_{R(0)}^{R(T)} \frac{f[x_o(t), y_o(t)] \ ds}{\left[\left(\frac{dx_o(t)}{dt} \right)^2 + \left(\frac{dy_o(t)}{dt} \right)^2 \right]^{-\frac{1}{2}}} \qquad (25)$$

14

which is the general expression for motion degradation with linear space invariant imaging system. The space invariant point spread function can be identified in Equation (25) as

$$h(x_i, y_i;\ x_o, y_o) = \left[\left(\frac{dx_o(t)}{dt}\right)^2 + \left(\frac{dy_o(t)}{dt}\right)^2\right]^{-\frac{1}{2}} \qquad (26)$$

Where $x_o(t)$, $y_o(t)$ are valid over the path of the object motion, that is,

$$x_o(0) \leq\ x_o(t) \leq\ x_o(T)$$
$$\qquad (27)$$
$$y_o(0) \leq\ y_o(t) \leq\ y_o(T)$$

and $h(x_i, y_i;\ x_o; y_o) = 0$ elsewhere.

From above discussion, we can find a solution to determine the blurring produced by linear camera motion. We will again describe the image $g(x_i, y_i)$ which is integrated by the camera sensor, as follows

$$g(x,y) = \int_0^T\ f[x_o - A(t),\ y_o - B(t)]\ dt \qquad (28)$$

Where $A(t)$ and $B(t)$ are the motion in x and y directions respectively. If we assume that camera is moved θ degrees off the horizontal axis and with a velocity of V_c, then the displacement distance in x and y directions at an instant time t will be

$$A(t) = V_c t \cos\theta$$

$$B(t) = V_c t \sin\theta \tag{29}$$

and

$$g(x,y) = \int_0^T f(x-V_c t \cos\theta, y-V_c t \sin\theta) \, dt \tag{30}$$

Taking Fourier transform of the both sides of Eq. (30) we obtain

$$G(u,v) = \int_0^T \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} f(x-V_c t \cos\theta, y-V_c t \sin)$$

$$\exp\{-j2\pi(ux+vy)\} dx \, dy \, dt \tag{31}$$

Making the change of variables

$$\varepsilon = x-V_c t \cos\theta$$

$$\eta = y-V_c t \sin\theta \tag{32}$$

we then have

$$G(u,v) = \int_0^T \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} f(\varepsilon,\eta) \exp\{-j2\pi(u\varepsilon+\eta v)\} d\varepsilon d\eta$$

$$\exp\{uV_c t\cos\theta + vV_c t \sin\theta\} \, dt$$

$$= F(u,v) \int_0^T \exp\{-j2\pi(uV_c t \cos\theta + vV_c t \sin\theta)\} \, dt \tag{33}$$

If we let d be the total displacement made by the camera in the
interval (0,T), then

$$d = V_c T \quad , \quad or, \quad V_c = \frac{d}{T} \tag{34}$$

and if we define "f" as

$$f = u \cos\theta + v \sin\theta \tag{35}$$

then, Eq. (33) becomes

$$G(u,v) = F(u,v) \int_0^T \exp\{-j2\pi f \frac{d}{T} t\} \, dt \tag{36}$$

as we can see, the OTF of the degradation equals to

$$H_d(u,v) = \int_0^T \exp\{-j2\pi f\frac{d}{T}t\} \, dt \tag{37}$$

Performing the integration in Eq. (37), we have

$$H_d(u,v) = \frac{T}{\pi f d} \, \sin \pi f d \, \, e^{-j\pi f d} \tag{38}$$

or

$$H_d(u,v) = T \, \text{Sinc}(fd) \, e^{-j\pi fd} \tag{39}$$

where $\text{Sinc}(fd) = \dfrac{\sin\pi fd}{\pi fd}$

OTF of Out-of-Focus Lens System

An aberration-free (diffraction limited) imaging system converts a diverging spherical wave into a spherical wave, that converges toward a point in the image plane. An aberration, such as defocusing, causes the exit wave to depart from its ideal spherical shape. In Figure 3,

17

O is an axial object point in the object plane and I is the geometrical
image of that point in the image plane. The energy radiated from the
point object O passes through the entrance and exit pupils and makes
an angle A with the optical axis in the image plane. The references
s. and s. are centered at O and I, respectively, and are of such
radii that they intersect the optical axis at the entrance and
exit pupils, respectively.

Figure 3   Imaging System Without Defect of Focus   (Ref. 8)

Figure 4   Imaging System with Defect of Focus   (Ref. 8)

In Figure 4, s' is the converging wave front exiting the exit pupil with a different spherical shape from its ideal shape and forms the image at the out-of-focus point P. The wave front s_2 converges to the in-focus point I. We can specify the amount of defocusing by the out-of-focus distance Z or the optical distance W between s_2 and s'.

The pupil function which describes the defocusing effect on the ideal spherical wave front is of the form (Ref. 8)

$$P(x,y) = \begin{cases} \exp\{jkw(x^2 + y^2)\} & , \text{ if } x^2 + y^2 \leq 1 \\ 0 & , \text{ if } x^2 + y^2 > 1 \end{cases} \qquad (40)$$

19

where $k = 2\pi/\lambda$ and W is the optical distance between the emergent wave front and the ideal spherical wave front measured along the extreme ray, and a convenient measure of the defect of focus. λ is the wave length. The coordinates (x,y) at exit pupil are normalized so that $x^2 + y^2 = 1$ at the edge of the pupil.

If the system has a circular aperture, then the OTF for such a system is a function of only one spatial frequency variable

$$H(s) = \frac{\int_{-\infty}^{\infty} \int_{-\infty}^{\infty} P(x + \frac{s}{2}, y) \, P^*(x - \frac{s}{2}, y) \, dx \, dy}{\int_{-\infty}^{\infty} \int_{-\infty}^{\infty} |P(x,y)|^2 \, dx \, dy} \tag{41}$$

The frequency s is a reduced frequency and related to normalized frequency $f = \sqrt{u^2 + v^2}$ by

$$s = \left(\frac{\lambda}{n \, SinA}\right) f \tag{42}$$

where n is the refractive index and taken to be 1 for all calculations in this study and the angle A is defined in Figure 4. The integrand in Equation (41) vanishes for s values outside the range $0 \leq |s| \leq 2$. The OTF for a defocused system can be found by inserting the pupil function of Eq. (40) into Eq. (41)

20

$$H_E(s) = \frac{4}{\pi a} \cos(\tfrac{1}{2}as) \left\{ bJ_1(a) + \sum_{k=1}^{\infty} (-1)^{k+1} \sin \frac{2kb}{2k} \left[J_{2k-1}(a) - J_{2k+1}(a) \right] \right\}$$

$$- \frac{4}{\pi a} \sin \left[\tfrac{1}{2}as\right] \sum_{k=0}^{\infty} (-1)^k \frac{\sin(2k+1)b}{2k+1}$$

$$\times \left[J_{2k}(a) - J_{2(k+1)}(a) \right] \tag{43}$$

where

$$a = \frac{4\pi}{\lambda} ws$$

$$b = \cos^{-1}(s/2) \tag{44}$$

and J_k is a Bessel function of first kind order k. These series are slowly converging. The OTF, $H_E(s)$, is the exact or diffraction OTF. Normalization in Eq. (40) assures that $H_E(0) = 1$, and as mentioned before, $H_E(s) = 0$ for s > 2. Because of the symmetry of the system, $H_E(s) = -H_E(s)$. From the symmetry properties of the Bessel functions, $H_E(s)$ is an even function of the defect of focus distance w.

The exact OTF obtained in Eq. (43) is difficult to calculate but, for small amounts of defocusing and small angles A, this function can be approximated to the geometrical OTF. The geometrical PSF of a defocused aberration free system with a circular aperture is simply a circular path of light of radius R (Ref. 14), that is

$$h(R) = CIRC(R) = \begin{cases} \dfrac{1}{\pi R^2} & , \quad R \le 1 \\ \\ 0 & , \quad R > 1 \end{cases} \qquad (45)$$

where $R = \sqrt{x^2 + y^2}$. The fourier transform of Eq. (45) will give us the geometrical OTF of the defocused system.

$$H_d(f) = \frac{J_1(2\pi r f)}{\pi r f} \qquad (46)$$

It is convenient to express the OTF in terms of the optical path length W and the normalized frequency s, because, the OTF can then be calculated without knowledge of the optical parameters of the system. A relation between W and the out-of-focus distance Z is required to calculate the OTF for a specific system. From the triangle IKP in Figure 4, we can write

$$(KP)^2 = (KI)^2 + (IP)^2 - 2(AI)(IP) \, Cos \, (\pi - A) \qquad (47)$$

This can be written as

$$(r'+Z)^2 = (r'+w)^2 + Z^2 - 2(r'+w) \, Z \, Cos \, (\pi - A) \qquad (48)$$

where the image distance OI = r'. Solving for W gives

$$W = -r' - Z \, Cos \, A + (r'^2 + 2r'Z + Z^2 Cos \, A)^{\frac{1}{2}} \qquad (49)$$

This equation can be approximated for small angles and small amounts of defocusing by

22

$$W = Z (1 - \text{Cos } A) \tag{50}$$

By using the trigonometric small angle approximation $\text{Sin } \frac{A}{2} = \frac{1}{2} \text{ Sin } A$, we find

$$W = \frac{1}{2} Z \text{ Sin}^2 A \tag{51}$$

We can again approximate the argument x of Bessel function in Eq. (46) by using Equations (41) and (51)

$$\begin{aligned} x &= 2\pi r f \\ &= \lambda \pi \text{ ws}/ \lambda \text{ CosA} \\ &= (4\pi/\lambda) \text{ ws} \\ x &= a \end{aligned} \tag{52}$$

Therefore,

$$H_d(s) = 2 \frac{J_1(x)}{x} \tag{53}$$

This equation should be normalized so that $H_d(0) = 1$, and represents the approximate OTF for a defocused optical system with circular aperture.

Noise Process

Observations of an image field are subject to measurement errors, irregularities of the recording media, and atmospheric light fluctuations. These phenomena give rise to a noise in the image. Noise in images can be divided into three categories: film grain

23

noise, photoelectronic noise, and thermal noise.

Film-grain noise is produced by a photographic emulsion during the process of image recording and reproduction. Under microscopic examination, the smooth tones of a photographic image assume a random, grainy appearance. Randomness is further introduced by the variable number of photons which expose a particular film grain and the varying size of the grains themselves. The subjective appearance of these factors in the image is called film-grain noise. For most practical purposes, film-grain noise can be modeled a Gaussian process (Ref. 4).

Photoelectronic noise is due to the statistical nature of light and of the photoelectronic conversion process inherent in image sensors. A model of this noise is given in Ref. 5.

Electronic noise is due to random thermal motion of electrons in resistive circuit elements and can be modeled as white Gaussian noise process; i.e., it has a flat power spectrum (Ref. 5.).

To restore a picture in the presence of noise, in addition to a knowledge of the degrading optical transfer function, we need to know (at least in theory) both the statistical properties of the noise and how it is correlated with the original image. In practice, the most common assumptions (like in the electronic communications) about the noise are that it is white, i.e., its power spectrum density is constant, and

it is uncorrelated with the original image (signal). Both these assumptions may be questioned. The concept of white noise is a mathematical abstraction, however, it is a convenient and reasonably accurate model, if the power spectrum density of the original image falls off much faster than the power spectrum density of the noise. As far as the noise and the original image being uncorrelated is concerned, there are examples of the noise which is correlated with the original image, e.g., in the case of film-grain noise (Ref. 4, 5). We will be mainly concerned with the noise which is uncorrelated with the original image and additive in the spatial frequency domain. Concerning the power spectrum of the noise, we will consider both cases where the noise is white and where it is colored in the spatial frequency domain. The latter will be modeled as a gaussian random variable with zero mean.

Different restoration methods may require different amounts of information about the noise process. Constraint image restoration methods (Ref. 7, 6) require that only the variance of the noise be known. On the other hand, the Wiener filter and power spectrum equalization filters require the characterization of the process in terms of its power spectral density or the ratio of the noise power spectrum density to the original image power spectrum density which we refer to as the noise-to-signal ratio (NSR). Since we will use Wiener filter and power spectrum equalization filter for restoration, we will estimate the NSR in spatial domain and in the

25

spatial frequency domain by assuming that the noise is additive and it is spatially stationary stochastic random process with zero mean.

Restoration Methods

As we mentioned earlier, image restoration is an estimation process that attempts to recover an original image from its degradations that were incurred while the image was being obtained. Restoration techniques are methods of obtaining a PSF (point spread function) for the restoration filter, so that the output of the restoration filter is a good estimate of the original image. We will assume that the degraded image $g(x,y)$ and the original image $f(x,y)$ obey the model given in Eq. (13). That is,

$$g(x,y) = \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} h(x-\gamma, y-\beta)\, f(\gamma,\beta)\, d\gamma\, d\beta + n(x,y) \qquad (54)$$

and Fourier transform of degraded image and restored image are given by Equations (15) and (16) respectively.

$$G(u,v) = H_d(u,v)\, F(u,v) + N(u,v) \qquad (55)$$

$$\hat{F}(u,v) = H_r(u,v)\, G(u,v) \qquad (56)$$

Inverse Filter.

In the absence of noise, Equation (55) reduces to

$$G(u,v) = H_d(u,v)\, F(u,v) \qquad (57)$$

26

or equivalently

$$F(u,v) = \frac{G(u,v)}{H_d(u,v)} \qquad (58)$$

since we want $\hat{F}(u,v) = F(u,v)$, Eq. (58) implies that

$$H_r(u,v) = \frac{1}{H_d(u,v)} \qquad (59)$$

and

$$\hat{F}(u,v) = H_r(u,v) \ G(u,v) = \frac{G(u,v)}{H_d(u,v)} \qquad (60)$$

This means that we can restore the degraded image g(x,y) by multiplying the Fourier transform G(u,v) of the degraded image by $H_r(u,v)$ and then inv rse Fourier transforming.

Some problems arise when one wants to use Eq. (60) in practice. There may be points or regions in the Fourier domain where $H_d(u,v) = 0$. In the absence of noise, as we can see from Eq. (57), the Fourier transform G(u,v) of the degraded image will also be zero, leading to undetermined ratios. Therefore, we can say that even in the absence of noise, it is, in general, impossible to restore f(x,y) exactly, if $H_d(u,v)$ has zeros in the Fourier domain. In the presence of noise, the zeros of G(u,v) and $H_d(u,v)$ will no longer coincide. When noise is present, we have

$$G(u,v) = H_d(u,v) \ F(u,v) + N(u,v) \qquad (61)$$

applying the restoration filter gives

$$\hat{F}(u,v) \;=\; G(u,v) \, H_r(u,v) \;=\; F(u,v) + \frac{N(u,v)}{H_d(u,v)} \tag{62}$$

If $H_d(u,v)$ is small or zero in any region of the Fourier domain where $N(u,v)$ is not correspondingly smaller or where $N(u,v)$ is non zero, then the contribution of the noise will be amplified, thus the term $N(u,v)/H_d(u,v)$ will have much larger magnitude than $F(u,v)$ and the inverse Fourier transform of $G(u,v)H_r(u,v)$ will be strongly influenced by these large terms. Instead, it will contain many noiselike variations and will not be meaningful restoration of $f(x,y)$.

Since the right-hand side of Eq. (60) cannot normally be evaluated numerically due to the zeros of $H_d(u,v)$, the most we can do is to restore only the frequencies in the Fourier domain where the noise-to-signal ratio is low. Such an alteration in the restoration process means that the exact inverse filter is not being performed; instead, an approximation is being made. This approximation can be improved to some degree by examining the output of the restoration filter. Let us denote the approximated inverse filter transfer function by $A(u,v)$. We can say that

$$H_r(u,v) \;\stackrel{\sim}{=}\; A(u,v) \tag{63}$$

If $H_d(u,v)$ does not have zeros and noise is not present, then the

28

restoration filter optical transfer function will be

$$H_r(u,v) = A(u,v) = \frac{1}{H_d(u,v)} \qquad (64)$$

Wiener Filter

The inverse filter performs poorly in the presence of noise since the noise process is not taken into account in the filter design. Inverse filtering also requires tedious manipulation of the inverse of the degrading transfer function. It would be preferable, if the filter itself controlled the noise amplification automatically. One way to design such a filter is to find a restoration filter transfer function that minimizes some measure of the difference between estimated image $f(x,y)$ and the original image $f(x,y)$. We will design a restoration filter that minimizes (in a statistical sense) the mean-squared error between the original image $f(x,y)$ and the estimated image $f(x,y)$. This filter is called least squares filter or Wiener filter.

Let the original image, the degraded image and the noise be represented by the stochastic random processes $f(r)$, $g(r)$, and $n(r)$ respectively. Where r is a position in the xy-plane. Then from the superposition integral in Eq. (9), we can write

$$g(r) = \int h_d(r-r') \, f(r') \, dr' + n(r) \qquad (65)$$

29

where dr' represents the area element dx'dy' in the xy-plane and $h_d(r)$ is the point spread function of the degradation. We need to solve the integral Equation (65) for the original image process f(r). However, with n(r) unknown, the Eq. (65) cannot be solved directly. The most we can do is to produce an estimate f(r) of the solution. We assume that f(r) and n(r) can be viewed as spatial stochastic processes, and assume that noise process n(r) is known. Then, the best estimate is to maximize the posterior probability density of f(r), given g(r), as defined Bayes's rule (Ref. 21). If we further assume that the estimate f(r) is a linear function of the gray levels in the degraded image process g(r), then the linear estimate f(r) can be expressed as

$$\hat{f}(r) = \int h_r(r-r')g(r') \, dr' \tag{66}$$

Our aim is to find a function $h_r(r)$, which is the point spread function of the restoration filter, such that mean-square error

$$\begin{aligned}
\varepsilon^2 &= E\{ [f(r) - \hat{f}(r)]^2 \} \\
&= E\{ [f(r) - \int h_r(r-r') \, g(r') \, dr']^2 \}
\end{aligned} \tag{67}$$

is minimized.

A function which satisfies

$$E\{ g(s)[f(r) - \int h_r(r-r') \, g(r') \, dr'] \} = 0 \tag{68}$$

for all positions r and s in the xy-plane will also minimize Eq. (67). From Eq. (68), we can write

$$\int h_r(r-r') \ E\{g(s) \ g(r')\}dr' \ = \ E\{g(s) \ f(r)\} \tag{69}$$

By using the definitions of the autocorrelation and cross-correlation of a random process (Ref. 9), we can re-write Eq. (69) as

$$\int h_r(r-r') \ R_g(s,r') \ dr' \ = \ R_{gf}(s,r) \tag{70}$$

We will further assume that the stochastic processes representing the image $f(r)$ and the noise $n(r)$ are (spatially) stationary. Therefore, the autocorrelation function $R_g(s,r')$ and cross-correlation function $R_{gf}(s,r)$ can be represented as $R_g(r'-s)$ and $R_{gf}(r-s)$, respectively; i.e., eq. (70) becomes

$$\int h_r(r-r') \ R_g(r'-s) \ dr' \ = \ R_{gf}(r-s) \tag{71}$$

for every position r and s in the xy-plane. By making variable changes: $r'-s = z'$ and $r-s = z$, we obtain

$$\int h_r(z-z') \ R_g(z') \ dz' \ = \ R_{gf}(z) \tag{72}$$

for all positions z in the xy-plane. We denote the coordinates of z by $(\Delta x, \Delta y)$ and of z' by (x,y) to obtain

$$\int_{-\infty}^{\infty} \int_{-\infty}^{\infty} h_r(\Delta x-x, \ \Delta y-y) \ R_g(x,y) \ dx \ dy = R_{gf} \ (\Delta x, \Delta y) \tag{73}$$

As we can see, the left-hand side of Eq. (73) is a convolution that is

$$h_r(x,y) \ * \ R_g(x, \ x+\Delta x; \ y, \ y+\Delta y) \ = \ R_{gf}(\Delta x, \ \Delta y) \tag{74}$$

31

or

$$h_r(x,y) * R_g(\Delta x, \Delta y) = R_{gf}(\Delta x, \Delta y) \qquad (75)$$

If we take the Fourier transform of both sides of Eq. (75) we have

$$H_r(u,v) S_g(u,v) = S_{gf}(u,v) \qquad (76)$$

or

$$H_1(u,v) = \frac{S_{gf}(u,v)}{S_g(u,v)} \qquad (77)$$

where $S_{gf}(u,v)$ and $S_g(u,v)$ are the Fourier transforms of $R_{gf}(u,v)$ and $R_g(u,v)$, respectively. $R_{gf}(\Delta x, \Delta y)$ is the spatial cross-correlation of the degraded image $g(x,y)$ and original image $f(x,y)$ and it is given by

$$R_{gf}(\Delta x, \Delta y) = E\{g(x,y) f(x+\Delta x, y+\Delta y)\} \qquad (78)$$

$$R_{gf}(\Delta x, \Delta y) = E\{[h_d(x,y) * f(x,y) + n(x,y)]$$

$$f(x+\Delta x, y+\Delta y)\} \qquad (79)$$

Since we assume that image process and noise process are uncorrelated and that the noise process has zero-mean, we have

$$E\{n(x,y) f(x+\Delta x, y+\Delta y)\} = E\{n(x,y)\} E\{f(x+\Delta x, y+\Delta y)\} = 0 \qquad (80)$$

and Equation (79) becomes

$$R_{gf}(\Delta x, \Delta y) = h_d(x,y) * R_f(\Delta x, \Delta y) \qquad (81)$$

Taking the Fourier transform of the both sides of Eq. (81) gives us

$$S_{gf}(u,v) = H_d^*(u,v) \, S_f(u,v) \tag{82}$$

where $S_f(u,v)$ is the power spectrum of the original image. It can easily be seen from Figure 2 that $S_g(u,v)$ is given by

$$S_g(u,v) = |H_d(u,v)|^2 \, S_f(u,v) + S_n(u,v) \tag{83}$$

where $s_n(u,v)$ is the power spectrum of the noise process. If we insert Equations (82) and (83) into Equation (77), we obtain

$$H_r(u,v) = \frac{H_d^*(u,v) \, S_f(u,v)}{|H_d(u,v)|^2 \, S_f(u,v) + S_n(u,v)} \tag{84}$$

Eq. (84) can be written in more convenient form as

$$H_r(u,v) = \frac{H_d^*(u,v)}{|H_d(u,v)|^2 + \dfrac{S_n(u,v)}{S_f(u,v)}} \tag{85}$$

This result gives the transfer function of Wiener filter that we will use as the restoration filter transfer function.

Power Spectrum Equalization Filter.

We modeled the degraded image as the output of a linear system which has the degrading transfer optical function $H_d(u,v)$. The input to this system is taken to be original image. From linear systems theory,

33

we can establish a relationship between the original image power spectrum and the degraded image power spectrum. From Figure 2 the power spectrum of the degraded image can be written as

$$S_g(u,v) = |H_d(u,v)|^2 S_f(u,v) + S_n(u,v) \tag{86}$$

Power spectrum equalization criterion states that the power spectrum of the estimated image be equal to the power spectrum of the original image. That is,

$$S_f(u,v) = S_{\hat{f}}(u,v) \tag{87}$$

where $S_{\hat{f}}(u,v)$ denotes estimated image power spectrum. It is possible to write $S_{\hat{f}}(u,v)$ in terms of $S_g(u,v)$ and the transfer function of the restoration filter

$$S_{\hat{f}}(u,v) = |H_r(u,v)|^2 S_g(u,v)$$

$$= |H_r(u,v)|^2 [|H_d(u,v)|^2 S_f(u,v) + S_n(u,v)|] \tag{88}$$

by substituting Equation (87) into Equation (88) and solving for $H_r(u,v)$ we obtain the transfer function of the restoration filter that performs the power spectral equalization as follows

$$H_r(u,v) = \left[\frac{1}{|H_d(u,v)|^2 + \dfrac{S_n(u,v)}{S_f(u,v)}} \right]^{\frac{1}{2}} \tag{88.1}$$

34

III. Parameter Estimation Techniques

Estimation of Degrading Transfer Function

We have seen several methods for restoring degraded images.
These methods require, as a description of the degradation, the
degrading point spread function (PSF) or its Fourier transform, the
degrading optical transfer function (OTF). However, in many practical
situations, a prior knowledge of the degrading PSF or OTF is not
available. Therefore, in order to apply one of these restoration
methods, one must first estimate the degrading OTF. Since we assume
that we do not have a prior information about the degradation and that
the original undegraded image is unavailable, we will consider the
estimation of the degrading OTF from the degraded image itself; i.e.,
so called "blind" restoration.

Method of Frequency Domain Inspection.

The degraded image in the absence of noise can be expressed as in
Eq. (57) in the frequency domain. It is given by point-by-point
product of the degrading OTF $H_d(u,v)$ and the Fourier transform of the
original image. Therefore, on the lines where $H_d(u,v)$ is zero, $G(u,v)$
will also be zero. If magnitude of $G(u,v)$ is displayed, these lines of
zero values can be determined, given that $H_d(u,v)$ is not zero in the
neighboring areas (Ref. 10). In the presence of noise, the displayed

35

values may not be exactly zero at these points, but the rough minima corresponding to ideal zeros can still be identified, if the noise is sufficiently small or white.

The identification of the zeros in the OTF may not be sufficient to determine the complete function. However, many of the common causes of the degradation such as the blurs due to a relative motion between camera and object or the out-of-focus camera have distinct zero patterns in their OTF's. We will ignore the unlikely possibility that the zeros of the Fourier transform of the original image have the same zero pattern, we will also assume that the degradation is due to either motion blur or out-of-focus camera. If the restored image looks reasonable, the confidence in the correctness of these assumptions increases. In the case t..at some prior knowledge of the OTF is available, this knowledge can be used in combination with the above method. For example, if the shape of the OTF is known, then only the frequency scale factor needs to be determined. In fact, in some degraded images, it is possible to determine the degradation form interactively. Once correct type of OTF is determined, the accuracy of its scale factor, in some cases, can be improved by averaging $|G(u,v)|$ or $|G(u,v)|^2$ along the lines parallel to the expected zeros and examining the resulting function.

In using this method, it is desirable to perform a simple linear spatial filtering operation such as differentiation on the degraded image before Fourier transforming it, in order to suppress the low

frequencies and to enhance the high frequencies. In most images, the amplitudes of the low frequency components are much greater than the amplitudes of the high frequency components. The above filtering operation may flatten the frequency spectrum of the degraded image and makes the identification of the zeros easier.

One such filter which meets the above objective is Laplacian operator $\nabla^2 = \partial^2/\partial x^2 + \partial^2/\partial y^2$. Since the Laplacian operator is linear and shift-invariant, applying it to the picture $g(x,y)$ is equivalent to convolving the degraded image $g(x,y)$ with the PSF $h_d(x,y)$ defined by (Ref. 11).

$$h_L(x,y) = \begin{vmatrix} 0 & 1 & 0 \\ 1 & -4 & 1 \\ 0 & 1 & 0 \end{vmatrix} \tag{89}$$

Visualization of the zeros in the spectrum can also be aided by taking the logarithm of the degraded image power spectrum. This operation may enhance the amplitude of dips due to the degrading transfer function. If the zeros are equally spaced, they produce a series of periodic spikes in the log power spectrum. The power spectrum of the log power spectrum, called the cepstrum, can be used for determining the exact spacing of the spikes and consequently the zeros of the degrading transfer function.

After visualization of the zeros, we need to recognize the zero pattern of the degrading OTF. In the case of linear camera motion, the zeros of the OTF requires a linear pattern. This pattern is the

zero crossing of the sinc function given by Eq. (39). That is, the zero pattern will be

$$f = \frac{1}{d} , \frac{2}{d} , \frac{3}{d} , \ldots \qquad (90)$$

The OTF of out-of-focus camera with circular aperture is given by Eq. (46) and its zeros will form a circular pattern about the origin which can be identified by (Ref. 10).

$$f = \frac{0.61}{r} , \frac{1.117}{r} , \frac{1.619}{r} , \frac{2.121}{r} , \ldots \qquad (91)$$

where $r = (u^2 + v^2)^{\frac{1}{2}}$.

If the ideal image consists of a very simple geometrical shape, then its Fourier transform may have a simple pattern of zeros that could be mistaken for the zeros in the OTF. In this case, the method described here may not work, unless a sufficient prior information to enable the separation of the zeros in the image from the zeros in the OTF is provided. But more-complex images would have more-random patterns of zeros in their Fourier transform, therefore this problem would be less likely to occur.

Image Segmentation.

Another approach to estimation of the degrading OTF, which has been studied by many researchers (Ref. 12, 13, 14, 15), is as follows: the degraded image is divided into M regions (subimages) which are all identical in size and they may overlap. If we assume

that the extent of the degrading point spread function $h_d(x,y)$ is small compared to that of each region of the degraded image, then approximately we have

$$g_i(x,y) = \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} h_d(x-\gamma, y-\beta) \, f_i(\gamma,\beta) \, d\gamma \, d\beta + n_i(x,y) \qquad (92)$$

where the index i denotes the i'th subimage. Since we can pre-process (low-pass filter) the degraded image to reduce the noise effects, we ignore the noise term in the right-hand side of Eq. (92). By taking the Fourier transform of the both sides of Eq. (92), we obtain

$$G_i(u,v) = H_d(u,v) \, F_i(u,v) \quad , \quad i = 1, 2, 3, \ldots, M \qquad (93)$$

The functions $G_i(u,v)$, $F_i(u,v)$, $H_d(u,v)$ are complex in the Fourier domain. Therefore, we may write Eq. (93) as

$$|G_i(u,v)| e^{j\theta_J(u,v)} = |H_d(u,v)| \cdot |F_i(u,v)| \cdot e^{j[\theta_H(u,v) + \theta_{fi}(u,v)]}$$
$$\qquad (94)$$

By taking the product average of the magnitudes over M regions, we will have

$$\prod_{i=1}^{M} |G_i(u,v)| = \left[\prod_{i=1}^{M} |F_i(u,v)| \right] \left[|H_d(u,v)| \right]^M \qquad (95)$$

it is possible to estimate the magnitude of the degrading OTF by (Ref. 13)

$$|H(u,v)| = \left[\prod_{i=1}^{M} |G_i(u,v)| \right]^{1/M} \Bigg/ \left[\prod_{i=1}^{M} |F_i(u,v)| \right]^{1/M} \qquad (96)$$

On the right-hand side of the Eq. (96), the denominator term

$\prod_{i=1}^{M} |F_i(u,v)|$, is not known. However, if the intensity

distributions in the M regions of the original image vary sufficiently

fast and are sufficiently different from one another, then we can

expect that this term will be approximately a constant. We also do not

have information about the phase of the estimated OTF. In most cases,

it might be reasonable to assume that the phase of

$\prod_{i=1}^{M} |F_i(u,v)|^{1/M}$ is approximately constant.

Another way of estimating the OTF by segmentation is to treat the

image as a (spatially stationary stochastic process (Ref. 14). From

the stochastic linear system relationship, we can write the power

spectrum of the degraded image in the i'th region as

$$S_{gi}(u,v) = S_{fi}(u,v) |H_d(u,v)|^2 + S_{ni}(u,v) \qquad (97)$$

After taking an average over the power spectrum of the subimages (the

square of the magnitude of the Fourier transform of the subimages), we

have an estimate of the power spectrum of subimages. Such an average

will retain much of the flavor of $|H_d(u,v)|$, since $|H_d(u,v)|$ is included

in each one of the averaged subimages, while each $F_i(u,v)$ and $N_i(u,v)$

are varying from subimage to subimage, thus, introducing a much more

subtle contribution to the average (Ref. 14). We may now search for

the zeros of $H_d(u,v)$ more successfully than we did in the frequency domain inspection method. Since most degraded images have reduced amount of high frequency power, the search for the zeros of $|H_d(u,v)|$ should be carried out along the dc axes of estimated $S_g(u,v)$. The power cepstrum which is defined as the Fourier transform of the logarithm of the power spectra $S_g(u,v)$ may enable us to identify exact spacing of the zeros of $H_d(u,v)$. The power cepstrum of Eq. (97) is equal to

$$P(u,v) \quad = \quad F\{\log S_f(u,v)\} \; + \; 2 \; F\{\log \; H_d(u,v)|\} \qquad\qquad (98)$$

Note that we have neglected the noise term. Since the right hand side of Eq. (98) results from an averaging process, $F\{\log S_f(u,v)\}$ retains little of the flavor of the original image while $2 \, F\{\log |H_d(u,v)|\}$ remains strongly characteristic of the degrading OTF. The rings of spikes, as previously mentioned, results from focus blur and the radius of these rings will be the parameter that we need to know to estimate the degrading OTF. In the case of motion blur, these spikes will be periodic in the direction of the motion and their pattern is given by Eq. (90).

Another approach which is similar to the method which is defined in Ref. 12 may be used for estimating the degrading OTF by segmentation method. By taking the complex logarithm of the both sides of Eq. (93), we have

$$CLOG[G_i(u,v)] = CLOG[F_i(u,v)] + CLOG \; [H_d(u,v)] \qquad\qquad (99)$$

Averaging over M subimages,

$$\frac{1}{M} \sum_{i=1}^{M} CLOG[G_i(u,v)] = \frac{1}{M} \sum_{i=1}^{M} CLOG[F_i(u,v)] + \frac{1}{M} \sum_{i=1}^{M} CLOG[H_d(u,v)] \quad (100)$$

We assumed that $H_d(u,v)$ is included in each subimage. Therefore we can write Eq. (100) as

$$CLOG[H_d(u,v)] = \frac{1}{M} \sum_{i=1}^{M} CLOG[G_i(u,v)] - \frac{1}{M} \sum_{i=1}^{M} CLOG[F_i(u,v)] \quad (101)$$

Since the right hand side of Eq. (100) results from an averaging proces and the term $CLOG[H_d(u,v)]$ is included by each subimage, the averaged term $\frac{1}{M} \sum_{i=1}^{M} CLOG[F_i(u,v)]$ retains little of the flavor of $CLOG[F_i(u,v)]$. If the term $\frac{1}{M} \sum_{i=1}^{M} CLOG[F_i(u,v)]$ was available, one could estimate the complex logarithm of the degrading OTF by Eq. (101). However, we must estimate the degrading OTF without a prior knowledge of the original image and the degradation. If the intensity distributions in the M regions of the original image are sufficiently different from one another, and if M is large enough (M >100), then it may be assumed that the term $\frac{1}{M} \sum_{i=1}^{M} CLOG[F_i(u,v)]$ converges to zero. Therefore, we have

$$CLOG[H_d(u,v)] = \frac{1}{M} \sum_{i=1}^{M} CLOG[G_i(u,v)] \quad (102)$$

$H_d(u,v)$ is then obtained by taking the antilogarithm i.e.,

$$H_d(u,v) \;=\; \exp\left\{ \frac{1}{M} \sum_{i=1}^{M} CLOG[G_i(u,v)] \right\} \tag{103}$$

We can estimate the magnitude of the degrading OTF by one of the above methods. We still need to estimate the phase of the degrading OTF. A method for this estimation is given in Ref. 15 and will be summarized here. After segmenting the degraded image and taking the Fourier transform of each segment, we have (Ref. Eq. 93)

$$\theta_{Gi}(u,v) \;=\; \theta_H(u,v) + \theta_{fi}(u,v) \tag{104}$$

By averaging over M regions,

$$\frac{1}{M} \sum_{i=1}^{M} \theta_{Gi}(u,v) \;=\; \theta_H(u,v) + \frac{1}{M} \sum_{i=1}^{M} \theta_{fi}(u,v) \tag{105}$$

Our hope was that the second term in the right-hand side of Eq. (105) would converge to a constant value. However, we can not make sure that this term converges to anything meaningful. Another method for estimating the phase (Ref. 15) is to form the product of subimages

$$G_i(u,v)\, G_i^*(u+\Delta u,\ v+\Delta v) \;=\; H_d(u,v)\, H_d^*(u+\Delta u,\ v+\Delta v)\, F_i(u,v)$$

$$F_i^*(u+\Delta u,\ v+\Delta v) \tag{106}$$

and taking average over M regions, we obtain

43

$$\frac{1}{M} \sum_{i=1}^{M} G_i(u,v) \ G_i^*(u+\Delta u, v+\Delta v) = H_d(u,v)H_d^*(u+\Delta u, \ v+\Delta v)$$

$$\frac{1}{M} \sum_{i=1}^{M} F_i(u,v)F_i^*(u+\Delta u, \ v+\Delta v) \qquad (107)$$

In Equation (107), we can calculate $\frac{1}{M} \sum_{i=1}^{M} G_i(u,v) \ G_i^*(u + \Delta u, \ v + \Delta v)$

from the degraded image by dividing the degraded image into M regions (subimages), and Fourier tansforming each subimage to form the auto-correlation product $G_i(u+v) \ G_i^*(u+\Delta u, \ v+\Delta v)$ (where Δu and Δv are constants for M subimages, and then averaging the resulting products by M. If a prototype image which is similar to the original image is available, then we can obtain a rough estimate of $\frac{1}{M} \sum_{i=1}^{M} F_i(u,v)$ $F_i^*(u+\Delta u, v+\Delta v)$ from the prototype image. An estimation of the product $H_d(u,v) \ H_d^*(u+\Delta u, \ v+\Delta v)$ can then be made by Eq. (107). For a lossless degration, which means the volume under $f(x,y)$ is equal to the volume under $g(x,y)$, we have $H_d(0,0) = 1$. Assuming that the products can be estimated and given $H_d(0,0) = 1$, we can obtain a recursive relationship where $H_d^*(u+\Delta u, \ v+\Delta v)$ is expressed in terms of $H_d(u,v)$

$$H_d^*(u+\Delta u, \ v+\Delta v) \ = \ \frac{\dfrac{1}{M} \sum\limits_{i=1}^{M} G_i(u,v) \ G_i^*(u+\Delta u, \ v+\Delta v)}{H_d(u,v) \dfrac{1}{M} \sum\limits_{i=1}^{M} F_i(u,v) \ F_i^*(u+\Delta u, \ v+\Delta v)} \qquad (108)$$

However, the stability of this expression is quite poor. For the phase of OTF, we have

44

$$\theta_{Gi}(u,v) - \theta_{Gi}(u+\Delta u,\ v+\Delta v) = \theta_{H}(u,v) - \theta_{H}(u+\Delta u,\ v+\Delta v)$$

$$+ \theta_{Fi}(u,v) - \theta_{Fi}(u+\Delta u,\ v+\Delta v) \quad (109)$$

If Eq. (109) is averaged in some sense over i, and if the average value of $[\theta_{fi}(u,v) - \theta_{Fi}(u+\Delta u,\ v+\Delta v)]$ can be estimated, then noting that $\theta_{H}(0,0) = 0$, we may estimate $\theta_{H}(u,v)$ as (Ref. 15).

$$\theta_{H}(u,v) = \theta_{H}(u,v) - [\theta_{Gi}(u,v) - \theta_{Gi}(u+\Delta u,\ v+\Delta v)]\ av$$

$$- [\theta_{Fi}(u,v) - \theta_{Fi}(u+\Delta u,\ v+\Delta v)]\ av \quad (110)$$

Line Estimation of the OTF.

Some degrading optical transfer functions such as motion blur in one direction can be described by a single line which may be estimated from the Fourier transform of the degraded image itself. To support this statement, consider the degrading OTF of the motion blur given by Eq. (39).

$$H_{d}(u,v) = T\ Sinc(fd)\ e^{-j\pi fd}$$

where $f = u\ Cos\theta + V\ Sin\theta$. If we assume that the relative motion between camera and object is in the horizontal direction ($\theta=0$), the Equation (39) becomes

$$H_d(u,v) = T \text{ Sinc}(ud) \, e^{-j\pi ud} \tag{111}$$

or for the motion in vertical direction ($\theta = \frac{\pi}{2}$)

$$H_d(u,v) = T \text{ Sinc}(vd) \, e^{-j\pi vd} \tag{112}$$

Since the right-hand side of the Eq. (111) does not depend on the vertical spatial frequency variable v, we can say that

$$H_d(u,v) = H_d(u) = T \text{ Sinc }(ud) \, e^{-j\pi ud} \tag{113}$$

Recall that the degraded image can be manipulated by a digital computer in N by N matrix form where the rows and columns of this matrix represent the spatial frequency variable v and u, respectively. In the absence of noise, the Fourier transform of the degraded image is equal to the point-by-point multiplication of the Fourier transform of the original image and the degrading OTF. Therefore, the degrading OTF and the original image matrices has to be identical in size. We can modify, Eq. (113) to write it in matrix form

$$H_d(k,\ell) = T \text{ Sinc}(ud) \, e^{-j\pi ud} \tag{114}$$

where k,ℓ denotes k'th column and ℓ'th row of the degrading OTF. And if the degraded image is represented by an NxN matrix, k and ℓ take values from 1 to N. If the function given by Eq. (114) is centered at N/2, then we can say

$$u = k - \frac{N}{2} \tag{115}$$

Equations (113) and (114) show that the degrading OTF, in this particular case, consists of identical rows (lines). Therefore, it will be sufficient to obtain a row of the degrading OTF.

In order to estimate a row of the degrading OTF, we will follow a procedure similar to the segmentation method. By taking the complex logarithm of the Fourier transform of the degraded image, we obtain

$$CLOG[G(k,\ell)] = CLOG[H_d(k,\ell)] + CLOG[F(k,\ell)] \qquad (116)$$

where $k,\ell = 1, 2, 3, \ldots, N$. Averaging over N rows, we have

$$\frac{1}{N}\sum_{\ell=1}^{N} CLOG[G(k,1)] = \frac{1}{N}\sum_{\ell=1}^{N} CLOG[H_d(k,\ell)]$$
$$+ \frac{1}{N}\sum_{\ell=1}^{N} CLOG[F(k,\ell)] \qquad (117)$$

We can write from Eq. (117)

$$\frac{1}{N}\sum_{\ell=1}^{N} CLOG[G(k,\ell)] = CLOG[H_d(k)] + \frac{1}{N}\sum_{\ell=1}^{N} CLOG[F(k,\ell)] \qquad (118)$$

In order to obtain an estimate of the first term, $CLOG[H_d(k)]$, in the right-hand side of Eq. (118), we need to know the second term, $\frac{1}{N}\sum_{\ell=1}^{N} CLOG[F(k,\ell)]$. Since right hand-side of Eq. (118) results from an averaging process, and the term $CLOG[H_d(k)]$ is constant while the term $CLOG[F(k,\ell)]$ is changing randomly from pixel to pixel on the same line (ℓ'th row), the resultant average term $\frac{1}{N}\sum_{\ell=1}^{N} CLOG[G(k,\ell)]$ retains

47

little of the flavor of CLOG[F(k,ℓ)]. If the term $\frac{1}{N} \sum_{\ell=1}^{N}$ CLOG[F(k,ℓ)]

can be neglected, then we have

$$\text{CLOG}[H_d(k) = \frac{1}{N} \sum_{\ell=1}^{N} \text{CLOG}[G(k,\ell)] \tag{119}$$

and

$$H_d(k) = \exp \frac{1}{N} \sum_{\ell=1}^{N} \text{CLOG}[G(k,\ell)] \tag{120}$$

If the light distribution in the degraded image varies sufficiently

fast, we can expect that the second term in the right-hand side of

Eq. (118) can be approximated by a constant. In this case, we

obtain

$$H_d(k) = \exp \frac{1}{N} \sum_{\ell=1}^{N} \text{CLOG}\,[G(k,\ell)] - c \tag{121}$$

where

$$c \approx \frac{1}{N} \sum_{\ell=1}^{N} \text{CLOG}[F(k,\ell)] \tag{122}$$

A prototype image which is similar to degraded image can also be used

for estimating $\frac{1}{N} \sum_{L=1}^{N}$ CLOG[F(k,ℓ)]. Let P(k,1) be the Fourier

transform of the prototype image, then we may assume that

$$\frac{1}{N} \sum_{\ell=1}^{N} \text{CLOG}[F(k,\ell)] \approx \frac{1}{N} \sum_{=1}^{N} \text{CLOG}[P(k,\ell)] \tag{123}$$

Since the degrading OTF ought to be identical in size to the degraded

image, we need to obtain a degrading OTF which is in the form of NxN

matrix from the estimated row, $H_d(k)$. This can be done by duplicating

$H_d(k)$ N times.

We have discussed another approach called "Line estimation of the OTF" to estimating the degrading OTF of the motion blur in one direction. It seems that it is possible to estimate the OTF of such a degradation from the degraded image itself by this method. The only problem in this approach seems to be the estimation of the term $\frac{1}{N} \sum_{\ell=1}^{N} \text{CLOG}[F(k,\ell)]$. We consider two cases to overcome this problem.

We first assumed that this term would converge to zero or a constant, and secondly we estimated it from a prototype image which is assumed to be similar to that of original image. However, we can say that both cases may contribute an error to estimated degrading OTF due to the estimation of $\frac{1}{N} \sum_{i=1}^{N} \text{CLOG}[F(k,\ell)]$. In order to avoid the estimation of the term $\frac{1}{N} \sum_{i=1}^{N} \text{CLOG}[F(k,\ell)]$, we will employ another approach which is similar to the frequency domain inspection method. Since the first term in the right-hand side of Eq. (118) converges to the complex logarithm of the degrading OTF, it may be possible to recognize the zero pattern of the degrading OTF correctly. The only parameter we need to know then is the total displacement distance d in Eq. (114). If the first zero of the pattern is "A" pixels (columns) away from the origin, then the total displacement distance d will be

$$d = \frac{1}{A} \tag{124}$$

After determining the parameter d of the Eq. (124), we can easily

49

calculate Eq. (114) for a given exposure time T.

Logarithmic Estimate.

In cases where the previous methods are not successful in estimating the degrading OTF, we can obtain an approximation by the following method. In the absence of noise, the complex logarithm of the Fourier transform of the degraded image is given by Eq. (116). For an NxN degraded image, we divide both sides of Equations (116) by N to obtain

$$\frac{1}{N} \text{CLOG}[G(k.\ell)] = \frac{1}{N} \text{CLOG}[H_d(k,\ell)] + \frac{1}{N} \text{CLOG}[F(k,\ell)] \qquad (125)$$

Since $H_d(k.\ell)$ is spatially invariant, the first term in the right-hand side of Eq. (125) will be the logarithm of the degrading OTF scaled by $1/N$, while the second term, $\frac{1}{N} \text{CLOG}[F(k\ell)]$, converges to a small number. Therefore, we may say that the right-hand side of Eq. (125) resembles the degrading OTF rather than the original image; i.e., a rough approximation of the degrading OTF is

$$H_d(k,\ell) = \frac{1}{N} \text{CLOG}[G(k,\ell)] \qquad (126)$$

Estimation of Noise-to-Signal Ratio.

The least-squares and the power spectrum equalization methods require the noise-to-signal power density ratio in the degraded image as a parameter. We can also say that these methods respond only to the

50

ratio of the noise-to-signal power density. Since we do not have a prior knowledge about the original image and the noise, we must estimate the NSR (noise-to-signal power ratio) from the degraded image itself.

Most of the researchers assume that the NSR is constant for all spatial frequencies. We may encounter different definitions of constant NSR, such as,

$$\text{NSR} = \frac{\text{STANDARD DEVIATION OF THE NOISE}}{\text{STANDARD DEVIATION OF THE SIGNAL}} \qquad (127)$$

where the original image is assumed to be corrupted by white Gaussian noise (Ref. 16). Another definition of the NSR is given by (Ref. 17).

$$\text{NSR} = 2x \frac{\text{STANDARD DEVIATION OF THE NOISE}}{\text{PEAK-TO-PEAK VARIATION OF THE IMAGE}} \qquad (128)$$

or it is defined (Ref. 22)

$$\text{NSR} = \frac{\text{STANDARD DEVIATION OF THE NOISE}}{\text{PEAK TO PEAK VARIATION OF THE IMAGE}} \qquad (129)$$

It is also possible to define the NSR as the variance of the noise process (Ref. 18), i.e.

$$\text{NSR} = 2\sigma_n^2 \qquad (130)$$

We can apply one of above equations to estimate the NSR; however, we first need to estimate the variance of the noise process and the original image. Consider a relatively noisy region in the degraded image. This region consists of the blurred image and additive noise.

Since the region is relatively noisy; i.e., it includes more noise

components than the blurred image components, the variance of this

region may resemble the variance of the noise rather than the

variance of the original image. Therefore, it is reasonable to assume

that the variance of a relatively noisy region in the degraded image

be approximately equal to the variance of the noise process. If we

pre-process (high pass filter) the degrading to enhance the high

frequency components than the original image does, and if the variance

is calculated over several noisy regions in the degraded image and the

resulting variances are averaged to obtain the noise variance, then

the confidence in above assumption increases. The Laplacian operator

may satisfy the objective of above pre-processing. Peak-to-peak

variation of the original image can be determined from the degraded

image interactively.

In our discussion of the various methods of estimating the NSR

from the degraded image, we have assumed that the noise process

is wide-sense spatially stationary stochastic process with zero mean

and is spectrally white, i.e., $S_n(u,v)$ = a constant. If $F(u,v)$ falls

off much faster in the spatial frequency domain than $S_n(u,v)$, correctness

of the white noise assumption increases. We will define the NSR as

NSR = (Average noise power)/(Average signal power)   (131)

Where average signal power refers to the average power contributed

by the original image.

Estimation in the Spatial Domain.

Since the noise and the original image are wide-sense spatially
stationary processes, their power density spectrum is defined by the
Fourier transform of their autocorrelation function (Ref. 9), that
is

$$S_n(u,v) \overset{\Delta}{=} \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} R_n(\Delta x, \Delta y)\{\exp -j2\pi(u\Delta x + v\Delta y)\} \, d\Delta x \, d\Delta y \qquad (132)$$

and

$$S_f(u,v) \overset{\Delta}{=} \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} R_f(\Delta x, \Delta y)\{\exp -j2\pi(u\Delta x + v\Delta y)\} \, d\Delta x \, d\Delta y \qquad (133)$$

It follows that the autocorrelation function is the inverse
Fourier transform of the power density spectrum.

$$R_n(\Delta x, \Delta y) = \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} S_n(u,v) \exp\{j2\pi(u\Delta x + v\Delta y)\} \, du \, dv \qquad (134)$$

and

$$R_f(\Delta x, \Delta y) = \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} S_f(u,v) \exp\{j2\pi(u\Delta x + v\Delta y)\} \, du \, dv \qquad (135)$$

From Equations (134) and (135), we can write

$$E\{|h(x,y)|^2\} = R_n(0,0) = \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} S_n(u,v) \, du \, dv \qquad (136)$$

and

$$E\{|f(x,y)|^2\} = R_f(0,0) = \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} S_f(u,v) \, du \, dv \qquad (137)$$

53

This means that the average noise power and original image power can be identified by their mean square value. Therefore, we may write Eq. (131) as

$$NSR = \frac{E\{|n(x,y)|^2\}}{E\{|f(x,y)|^2\}} \tag{138}$$

since the mean value of the noise is zero, the numerator of the Eq. (138) is equal to

$$E\{|n(x,y)|^2\} = \sigma_n^2 \tag{139}$$

where σ_n^2, variance of the noise, can be estimated from a relatively noisy region in the degraded image. If a prototype image which is similar to that of original image is available, then we may estimate the denominator term in Eq. (138) from the prototype image $p(x,y)$.

$$E\{|f(x,y)|^2\} = E\{|p(x,y)|^2\} \tag{140}$$

However, our primary aim is to estimate all necessary parameters of restoration filter from the degraded image itself. The degraded image may be expressed as

$$g(x,y) = f_b(x,y) + n(x,y) \tag{141}$$

where

$$f_b(x,y) = h_d(x,y) * f(x,y) \tag{142}$$

If we assume that the average powers contained by $f_b(x,y)$ and $f(x,y)$ are approximately equal, then we may say that

$$E\{|f_b(x,y)|^2\} \approx E\{|f(x,y)|^2\} \qquad (143)$$

We can now estimate the NSR from the degraded image itself as follows

$$E\{|f(x,y)|^2\} = E\{|g(x,y)|^2\} - E\{|n(x,y)|^2\} \qquad (144)$$

where the noise and the original image are assumed to be statistically independent. By using equations (141), (139), (143), and (144) we may obtain,

$$NSR = \frac{\sigma_n^2}{E\{|g(x,y)|^2\} - \sigma_n^2} \qquad (145)$$

where the numerator and denominator denote the noise and original image average power, respectively. If σ_n^2 is small compared to $E\{|g(x,y)|^2\}$, then Eq. (140) can be approximated as

$$NSR = \frac{n^2}{E\{|g(x,y)|^2\}} \qquad (146)$$

Estimation in the Frequency Domain.

It is also possible to estimate NSR in the spatial frequency domain. The power density spectrum of the degraded image is given by

$$S_g(u,v) = |H_d(u,v)|^2 S_f(u,v) + S_n(u,v) \qquad (147)$$

where $S_n(u,v)$ is constant for all spatial frequencies u and v and is approximately equal to the variance, i.e.,

55

$$S_n(u,v) \approx \sigma_n^{\ 2} \qquad \qquad (148)$$

By substituting Eq. (148) into Eq. (147) and solving for

$S_n(u,v)/S_f(u,v)$, we obtain

$$NSR = \frac{S_n(u,v)}{S_f(u,v)} = \frac{|H_d(u,v)|^2}{S_g(u,v) - \sigma_n^{\ 2}} \ \sigma_n^{\ 2} \qquad (149)$$

Since the only constant in above equation is $\sigma_n^{\ 2}$, the NSR will depend

on the spatial frequencies u and v. If the degrading OTF is zero at

any spatial frequency, then the NSR becomes zero and leads the

restoration filter to undetermined ratio. In order to see this effect,

we may insert Eq. (149) into the Eq. (85) which the OTF of the

Wiener filter.

$$H_r(u,v) = \frac{H_d^{\ *}(u,v)}{|H_d(u,v)|^2 + \dfrac{|H_d(u,v)|^2 \sigma_n^{\ 2}}{S_g(u,v) - \sigma_n^{\ 2}}} \qquad (150)$$

If $H_d(u,v) = 0$, then $H_r(u,v) = 0/0$ which is undetermined ratio that

we encountered in the inverse filtering method. We can avoid this by

modifying Eq. (150) so that

$$H_r(u,v) = \begin{cases} \dfrac{H_d^{\ *}(u,v)}{|H_d(u,v)|^2 + \dfrac{|H_d(u,v)|^2 \sigma_n^{\ 2}}{S_g(u,v) - \sigma_n^{\ 2}}} & , \ \text{if} \ |H_d(u,v)| > R \\[4em] 1 & , \ \text{if} \ |H_d(u,v)| < R \end{cases}$$

$$(151)$$

where R=0. Since we cannot recover the zeros of the $G(u,v)$,

Eq. (161) can be considered as a reasonable approximation to the

Wiener filter. In the absence of noise, it performs as an inverse

filter. Otherwise, it deemphasizes the noise component in the

degraded image.

IV. <u>Results</u>

In order to be able to compare the degrading OTF estimated by one of the methods we discussed with the exact OTF, we may generate a degrading OTF and convolve it with an image to produce a degraded image and then estimate the degrading OTF assuming a little or no prior knowledge about the degradation.

To accomplish the above task, we need to define the spatial domain and the spatial frequency domain. We used 256x256x4-bit images represented by a matrix of 256 rows and 256 columns with each element of this matrix corresponding to a pixel in the picture and each pixel taking on gray-scale values from 0 (black) to 15 (white). In the frequency domain, the discrete Fourier transform of the image is represented by a 256x256 matrix of complex values. Both the spatial (space) domain and the spatial frequency domain representations are centered at the 128'th row and 128'th column of the matrices, i.e., it corresponds to (x=0, y=0) in the spatial domain and (u=0, v=0) in the spatial frequency domain.

A simple computer graphics program was then implemented in FORTRAN 5 to generate an image. This program enables us to draw lines from one point to another and circles centered at a point in the spatial domain. For example, the instructions below will draw a line from (x=-50, y=-50) to (x=50, y=50) with the intensity level 14, and a circle

at the center (x=0, y=0) with radius of 10 and the intensity level 7, respectively,

        call LINE(IBUF,14,-50,-50,50,50)

        call CIRCLE(IBUF,7,0,0,10)

where IBUF is an array used to hold the picture file (see Ref. 19). A test image was generated using this program and is shown in Picture 1.

To characterize the degrading system which we described in Chapter II, "Image Restoration System Model", we need to generate a point spread function or an optical transfer function. We implemented Eq. (112) to obtain the OTF of the motion blur in one direction. As we can see from Eq. (112), it only depends on the frequency variable "u" which corresponds to the vertical direction and takes values from -127 to 127 in the frequency domain that we described above. Picture 2 shows the OTF of the degrading system obtained from Eq. (112) for T=1.0, and d=0.021.

The degraded system is then used to obtain a degraded image. This degrading system simply convolves its point spread function with the input (original image) in the spatial domain. Since the convolution in the spatial domain is equivalent to point-by-point multiplication in the spatial frequency domain, the process of convolving the input (original image) picture with the PSF (point spared function) to produce the output (blurred image) is equivalent to first computing the Fourier transform of the input (original image) then multiply it with the OTF (optical transfer function) point-by-point.

59

and then computing the inverse Fourier transform of the result to
produce the output (blurred) image. This process is summarized by
Figure 6 where 2DFFT, and $2DFFT^{-1}$ denote forward and inverse two-
dimensional Fast Fourier transform, respectively and "X" denotes
point-by-point multiplication. Picture 3 shows the output of this
degradation process for the input image of Picture 1.

Figure 5   The Degrading (Blurring) Process

We applied all filtering techniques in the Fourier domain.
The input and output picture files of the two-dimensional Fast Fourier
Transform software that we used were required to be complex picture
files, while the input/output picture files of the Octek Image Analyzer
system which we used for display of the pictures on a monochrome video
monitor were required to be 4-bit integer picture files. Therefore,
the process of any of the filtering operations that we will discuss
next require the conversion of pictures from integer to complex form
and vice versa. A general purpose filtering operation is summarized
in Figure 6 where VTC and CTV refer to the video-to-complex and

complex-to-video conversion processes, respectively. The filter

parameters are the NSR and the degrading OTF.

Figure 6 Filtering Operation

With our implementation on the AFIT Signal Processing Lab's Data

General Eclipse S/250 16-bit minicomputer: it takes approximately 36

minutes (except for the estimation of the parameters of the filter) to

process a 256x256 input picture by a Wiener filter using above

algorithm described in Figure 6. We will now attempt to estimate

the degrading OTF from the degraded image by means of the estimation

methods described in previous sections.

As we mentioned in the method of frequency domain inspection,

we may pre-process the degraded image to reduce the noise effects.

However, we can see by looking at Picture 3 that there is no apparent

noise present. Therefore, we simply compute the Fourier transform

$G(u,v)$ of the degraded image without pre-processing. Picture 4 shows the

plot of $G(u,v)$. The dark (black) points corresponds to the zeros of

the $G(u,v)$. Before examining the zeros of the $G(u,v)$, we will turn

our attention back to the degraded image (Picture 3). We see that this

image is blurred only in vertical direction, i.e., it contains a spread

in one direction only. Based upon this observation, we will assume that the degradation is due to motion blur in one direction which we described earlier. If this assumption is true, then we must be able to find a zero pattern in the Fourier transform of Picture 3 which corresponds to the zeros of the sinc function given by Eq. (90). Since the blur is in vertical direction, we should search for the zero pattern in the vertical direction in the plot of $G(u,v)$ shown by picture 4, and determine the first zero of the degrading OTF. There are first zeros located 34, 36, 42, 46, 48, and 54 pixels away (see Picture 4) from the origin which obey the zero pattern given by Eq. (90). However, only one of these zeros should be the first zero of the degrading OTF given by Eq. (112). In order to determine the correct first zero, we may pick one of those zeros, obtain the degrading OTF by Eq. (112), and restore the degraded image. If the first zero that we chose is not the correct one, the output of the restoration system (e.g., inverse filter) will not be a meaningful picture and we should repeat the process with another choice until we find the zero that produces the "best" restoration. The parameter d of the degrading OTF given by Eq. (112) is found by

$$d = 1/|\text{the first zero distance}| \qquad\qquad (152)$$

A value of d = 1/4b gives the best restoration of Picture 3 by inverse filtering. The degrading OTF obtained by Eq. (112) for the parameter d = 1/4b is shown by Picture 5, and the image restored by the inverse filter is shown in Picture 6. When we examine the

restored image (Picture 6), we see noise-like amplification artifacts,
in addition to restored degradations. These artifacts are due to the
ill-conditioned behavior of the inverse filter. We will consider
this problem later. When the possible zero patterns become too many,
it takes too much time and effort to find the correct zero pattern
by this trial-and-error.

Since we concluded from the degraded image (Picture 3) that the
degradation is due to the motion in vertical direction, we can employ
the line estimation method described in Chapter III, section entitled
"Line Estimation of the OTF." If Equation (118) is modified
for motion in the vertical direction as

$$\frac{1}{N} \sum_{k=1}^{N} CLOG[G(k,\ell)] = CLOG[H_d(\ell)] + \frac{1}{N} \sum_{k=1}^{N} CLOG[F(k,\ell)] \qquad (153)$$

If the term $\frac{1}{N} \sum_{k=1}^{N} CLOG[F(k,\ell)]$ is assumed to converge to zero, then

$H_d(\ell)$ is given by

$$H_d(\ell) = \exp\{\frac{1}{N} CLOG[G(k,\ell)]\} \qquad k = 1, 2, \ldots, N. \qquad (154)$$

As we can see from the Eq. (154) $H_d(\ell)$ is a column obtained
by averaging the columns of the matrix which represents the complex
logarithm of the $G(u,v)$, and calculating the antilogarithm of the
average. Since the degraded image is 256x256 in size, N is, in this
case, equal to 256 and $H_d(\ell)$ is an array (column) with 256 elements. To
estimate the first element of the $H_d(\ell)$ corresponding elements of the 256
columns of this matrix should be summed and averaged and then

antilogarithm of this average should be calculated. This method was implemented to estimate $H_d(\ell)$ from the complex logarithm of $G(u,v)$. $H_d(\ell)$ is then duplicated N times to obtain the NxN matrix of the degrading OTF. Picture 7 shows the estimated degrading OTF. It seems like a sinc function, but the intensity variations do not obey a sinc function variations due to the term, $\frac{1}{N} \sum_{k=1}^{N} CLOG[F(k,\ell)]$, which we assumed to be zero. However, we may obtain an exact sinc function which has its first zero identical to that of Picture 7. This exact sinc function is shown by picture 8 and it is assumed to be the degrading OTF. The degraded image is restored by inverse filter and it is shown by Picture 9. We can see the ill-conditioned behavior of exact inverse filter in the Picture 9. We then modified the inverse filter as follows

$$H_r(u,v) \cong A(u,v) = \begin{cases} \dfrac{1}{H_d(u,v)} & , \quad \text{if } H_d(u,v) \geq R \\ \\ 1 & , \quad \text{if } H_d(u,v) < R \end{cases} \qquad (155)$$

Restored pictures using Eq. (155) for different R values are listed below

Picture 10	R = 0.000999
Picture 11	R = 0.009999
Picture 12	R = 0.099999
Picture 13	R = 0.02

Table 1   Restored Pictures and R Values of Eq. (155)

As we can see from the these restored pictures, it is possible to overcome the ill-conditioned behavior of the inverse filter. For small values of R, the ill-conditioned behavior still exists, while the degradation is no longer restored for the large values of R. We could, therefore, find an "optimum" value of R interactively.

The degraded image (Picture 3) that we restored in the preceding experiment was a binary (two-intensity level) picture generated by computer. We next applied the methods developed in Chapter III to the degraded image shown in Picture 14. This picture was digitized from photographic film taken a hand held 35 mm camera. The picture is a blurred image of the masking of an aircraft fuselage. It includes more than two intensity levels with maximum and minimum intensity levels, 14, 0, respectively. Its mean, meansquare, and variance are calculated to be 5.11, 34.43, 9.84, respectively. Since no detailed information was available on how the image was acquired, we assume no prior information about the degradtion. Therefore, we must estimate all essential parameters from the degraded image itself. It is not possible to determine or assume the form of the degradation by looking at the degraded image (Picture 14). But, we can see that it contains noise. Therefore, we will first apply the Laplacian operator to the degraded image. Picture 15 shows the degraded image after the Laplacian operation. We next take the Fourier transform of Picture 15. The magnitude of the Fourier transform presented in Figure 7 shows circles of zeros of $|G(u,v)|$ centered about the origin. The first and second zero

are located $R_1 = 3$ and $R_2 = 6$ pixels away from the origin, respectively. The ratio of R_1 to R_2 becomes

$$\frac{R_1}{R_2} = \frac{3}{6} = 0,5 \qquad (156)$$

The degrading OTF of out-of-focus camera with circular aperture forms approximately periodic circular zero pattern and it is given by Eq. (91). The ratio of the first zero of this pattern to its second zero is equal to

$$\frac{\text{THE FIRST ZERO}}{\text{THE SECOND ZERO}} = \frac{0.61}{0.117} = 0.546106 \qquad (157)$$

which is approximately equal to the ratio R_1/R_2. Therefore, we will assume that the degradation is due to out-of-focus camera with circular aperture and its degraded OTF is of the form of Eq. (46). The parameter r of Eq. (46) is obtained from the relationship

$$\frac{0.61}{r} = 3 \qquad (158)$$

and then

$$r = \frac{0.61}{3} = 0.2033 \qquad (159)$$

Implementation of Eq. (46) requires us to calculate the Bessel function of first kind of order n. These series expansion of $J_n(x)$ is given by (Ref. 20)

	123	124	125	126	127	128	129	130	131	132	133	134	135	136	137
123!	O	O	O	O	O	O	O	O	O	O	O	O	O	O	O
124!	O	O	O	O	O	O	O	O	O	O	O	O	O	O	O
125!	O	O	O	O	1	1	1	1	O	O	O	O	O	O	O
126!	O	O	O	O	1	O	O	O	1	O	O	O	O	O	O
127!	O	O	O	1	O	O	O	O	O	1	O	O	O	O	O
128!	O	O	1	1	O	1	1	1	O	1	O	O	O	O	O
129!	O	O	1	O	1	3	15	3	1	O	1	O	O	O	O
130!	O	O	O	1	O	1	1	1	O	1	1	O	O	O	O
131!	O	O	O	1	O	O	O	O	O	1	O	O	O	O	O
132!	O	O	O	O	1	O	O	O	1	O	O	O	O	O	O
133!	O	O	O	O	O	1	1	1	1	O	O	O	O	O	O
134!	O	O	O	O	O	O	O	O	O	O	O	O	O	O	O
135!	O	O	O	O	O	O	O	O	O	O	O	O	O	O	O
136!	O	O	O	O	O	O	O	O	O	O	O	O	O	O	O
137!	O	O	O	O	O	O	O	O	O	O	O	O	O	O	O

Figure 7　The Zeros of $|G(u,v)|$

67

$$J_n(x) = \sum_{k=0}^{N} \frac{(-1)^{2k} (x/2)^{n+2k}}{k! \ \Gamma(n+k+1)} \tag{160}$$

where $x = 2\pi rf$, and $f = \sqrt{u^2 + v^2}$. The spatial frequency domain

that we defined at the beginning of this chapter is normalized

by 127 so that the spatial frequency variable can take values

from -1.0 to 1.0. This enables the Bessel function to converge to

zero. Eq. (46) is then calculated for N+50, n=1, and r = 0.2033 to

obtain the degrading OTF shown by Picture 16.

After estimating the degrading OTF, we next need to estimate the

NSR in the degraded image. If the NSR is defined by Eq. (146), i.e.,

$$NSR = \frac{\sigma_n^2}{E\{|g(x,y)|^2\}}$$

where $E\{|g(x,y)|^2\}$ is the mean square value of the degraded image

(Picture 14) and is computed to be equal to 34.43, and the variance

of the noise is calculated from a relatively noisy region shown in

Picture 17 to be 5.91. Then, the NSR becomes 0.172. Picture 18

shows the image restored by the Wiener filter with degrading OTF

of Picture 16 and the NSR of 0.172. Another way to obtain the degrading

OTF is to obtain the degrading point spread function. The Fourier

transform of the degrading point spread function gives us the

degrading OTF. The degrading point spread function given by

Eq. (45) is calculated for R = 0.203 (shown in Picture 19), then Fourier

68

transformed to obtain the degrading OTF shown in Picture 20.
Picture 21 shows the restored image obtained by Wiener filter with this
degrading OTF (Picture 20) and the same NSR (0.172).

We also tested another approach to estimating the degrading OTF
presented in Eq. (126). Since the degraded image is 256x256, the
parameter N of Eq. (126) is equal to 256. With the degrading OTF
estimated by Eq. (126) and the NSR of 0.172, the degraded image is restored
by Wiener filter. Picture 22 shows the restored image. As we can see,
it is possible to restore some degradation, but most of the degradation
is unrestored. We estimated the NSR by Eq. (149) and used the same OTF
to obtain restoration filter OTF given by Wiener filter. Restored images
with different NSR's are listed below

<div style="text-align:center">

Picture 23 $S_n(u,v) = 5.91$

Picture 24 $S_n(u,v) = 2.4$

Picture 25 $S_n(u,v) = 1.55$

Table 2   Restored Pictures and Noise Variances

</div>

Where $S_n(u,v)$ is the noise power required by Eq. (149) to estimate
the NSR. We assumed that the noise is Gaussian random process with
zero mean and the variance obtained from the noisy region (see Picture 17)
equal to 5.91. The autocorrelation of the noise R_n in the degraded
image is estimated by

$$R_n = 0.164 \exp \left\{ - \frac{1}{11.8} (x^2 + y^2) \right\} \tag{161}$$

noise power is obtained by

$$S_n(u,v) = |F\{R_n\}|$$ (162)

The NSR is then estimated by Eq. (149). The restored image is shown in Picture 26. In order to avoid unwanted artifacts in the restored images with the NSR obtained from EQ. (149), we used modified Wiener filter OTF given by Eq. (150) and obtained restored images using different values of R values with the same NSR value (see Pictures 27, 28). The NSR was estimated by Eq. (149) for $S_n(u,v) = \sigma_n^2 = 5.91$.

Another approach to estimation of the degrading OTF is the line estimation method described in the previous chapter. Although it was developed for linear motion blur in one direction, we will use it for estimating the degrading OTF of the degraded picture. This degrading OTF consists of only a line either in vertical direction or horizontal direction. A line in vertical direction can be estimated from the degraded image itself by Eq. (120). In this case, we have

$$H_d(k) = \exp\{\frac{1}{256} \sum_{k=1}^{256} CLOG[G(k,\ell)]\}$$ (163)

where k = 1, 2, 3,...., 256. The degrading OTF obtained by Eq. (120) is shown in Picture 29. The degraded image is restored by Wiener filter with the NSR of 0.172, and shown in Picture 30. Secondly, A line in horizontal direction is estimated by

$$H_d(\ell) = \exp\{\frac{1}{256} \sum_{k=1}^{256} CLOG[G(k,\ell)]\}$$ (164)

and is shown in Picture 31. The degraded image is restored by Wiener

filter with the same NSR(0.172) and it is shown in Picture 32. As we

can see, it is possible to restore most of the degradation in the

degraded image. Therefore, we generated a sinc function (Eq. (112) with a

first zero (d=1/32, T=1.0) is taken to the equal to tnat of Picture 31.

Pictures 33 and 34 show the sinc function and the restored image by

Wiener filter with the same NSR(0.172), respectively, Some

degradation still is present while most of the high frequencies are

emphasized in the restored image (Picture 34).

We finally tried to estimate the degrading OTF by segmentation method

which we described in Chatper III. The degraded image is divided into

169 subimages which are all 64x64 in size. This is done by forming a

window which is 64x64 in size, then its left-hand corner placed at the left

hand-corner (first row and first column) of the degraded image, and

subimages are obtained shifting this window by a shifting factor 16

pixels in this particular case toward right and down on the degraded

image. Each subimage is Fourier transformed to form the Eq. (93).

Eq. (96) is calculated by muliplying the magnitude of the Fourier transfor

of each subimage point-by-point, then taking 1/M power of each resultant

point and dividing by the term $[\prod_i^M F_i(u,v)]^{1/M}$ which is assumed to be

constant and equal to 1.0. We were not able to restore the degraded image

by using the resulting OTF. The same algorithm was implemented for different

constant values, but, it was still not possible to obtain a meaningful

degrading OTF.

We next estimated the power spectra given by Eq. (97) by averaging the magnitude square of the Fourier transform of each subimage over 169 subimages. Then the power cepstrum of this estimate is obtained. The spikes occur periodically as in motion blur and they are along the horizontal direction (the degraded image (Picture 14) seems to be blurred in both horizontal and vertical directions through). The first spike is 4 pixels away from the origin. We assumed the degradation was due to motion in horizontal direction and calculated the degrading OTF given by Eq. (111) for d=0.25 it was not possible to obtain a meaningful restoration.

Another attempt to estimate the degrading OTF was made by using Eq. (103). The degraded image was divided into 49 subimages by shifting the 64x64 window for 32 pixels in horizontal and vertical directions. Each subimage was Fourier transformed and the complex logarithm of the Fourier transform of each subimage taken to form Eq. (99). The degrading OTF was then estimated by taking the average over 49 subimages and taking anti-logarithm to calculate Eq. (103). The resultant degrading OTF seemed like a sinc function with its minimum at 18 pixel away from the center. We again generated a sinc function by Eq. (112) and used this as the degrading OTF (shown in Picture 35), and with the same NSR(0.172). The restored image is shown in Picture 36.

To be able to test the methods that we described in Chapter III for the estimation of the NSR, we used a Vidicon camera and the blurred image shown by Picture 4. The vidicon camera was oriented to a flat surface and

a picture was acquired. The light distribution on the flat surface

was made as uniform as possible. Our aim was to obtain a noise source

which might reflect the characteristics of the noise process that we

discussed in Chapter II section entitled "Noise Process". The noise

picture was then processed (Laplacian operator applied) to emphasize its

high frequency components and subtracted the mean. The processed noise

image is shown in Picture 37. Then the blurred image (Picture 3) and

the noise image was added together to obtain the noisy, degraded image

shown in Picture 38. Then we used the estimation methods that we describe

in the spatial domain and the spatial frequency domain. A noisy region

is selected as in labeled in picture. The variance over this region was

calculated as 14.7376 and the mean square calculated over the picture

as 65.8043. Then the degraded image (picture 38) was restored by

Wiener filter using the degraded OTF shown in Picture 5, and the

NSR estimated by Eq. (103) as 0.2. The restored picture is shown

in Picture 40. As we can see most of the noise in the degraded image

(Picture 38) is reduced in the restored image (Picture 40) while some

of blur is left unrestored. This is because we assumed that the power

spectrum density is white, i.e., constant and equal to the variance

: the noise to derive a method to estimate the NSR in Chapter III.

However, this is not true in reality in this case and the restored

is optimal. Picture 41 shows the image restored by power

spectration filter using the same degrading OTF and the

the reduced noise in the restored image. There

improvement in the restoration.

Two main approaches to estimating the degrading OTF have been presented in this thesis. First, we determined the form of the degrading OTF and whether it is due to linear camera motion or out-of-focus camera, then determined the necessary parameters to estimate the degrading OTF. Secondly, the degrading OTF was estimated directly from the degraded image. Methods to estimate the NSR have been defined in spatial domain and in spatial frequency domain.

A trivial solution to the first approach was the method of frequency domain inspection. However, this method required that the degrading OTF must be oscillatory and the image must contain appreciable high frequency components, well distributed, so that the zeros in the degrading OTF can be identified. Furthermore, the NSR must be small enough not to abscure the zeros; otherwise, it may become impossible to determine its parameter (i.e., to recognize the zero pattern) unless a prior knowledge about the original image is available. The degraded image shown in Picture 3 satisfied these requirements. There were six possibilities for the first zero of the degrading OTF that we were searching for. We had to try each one of them and find out the one which restores the degraded image best. The line estimation method was then implemented to estimate the degrading OTF. We could not estimate the exact degrading OTF due to the term contributed by the original image. However, we were able to determine the first zero of the degrading OTF. This method resulted in a considerable saving in time and effort over that required by the frequency domain inspection method. It takes six minutes run time for the spatial

which implements line estimation method while it takes more than an hour for the frequency domain inspection to analyze and determine the parameters of the degrading OTF. The degraded image (Picture 3) was then restored by an inverse filter. We modified the inverse filter to avoid the ill-conditioned behavior. It was possible to restore most of the information which was lost due to the blur. If we compare the degraded image (Picture 2) with the original image (Picture 1), most of the information in the circles and the upper parallel lines of the squares are lost. One can no longer say that they are parallel lines. In the restored pictures, these lines and circles, including tiny details, are recovered. This includes the highest possible frequency data, the upper parallel lines of the inside square which are one pixel away from each other. However, the restored images do not look as pleasant and clear as the original image does. They include noise like variations. We had to compromise at this point, since we could not implement the exact inverse filter. On the other hand, it may be considered more important to recover the information which is lost than to obtain a more pleasant picture. Once the lost information is recovered, it then can be processed with the constraints of the human eyes to improve the quality of the restored image.

We also used line estimation method on the degraded image shown in

hand side of the Eq. (160) is theoretically defined for infinite
number of terms which we calculated it for 50 terms. But this did not
contribute a significant error to the restored pictures. The same
degrading OTF is calculated by the aid of the Fourier transform. The
degrading point spread function was calculated and then Fourier trans-
formed to obtain the degrading OTF. Some improvement was obtained in
the restoration. The segmentation methods which are successfully used to
restore the degraded images by related references were applied to
estimate the degrading OTF from the degraded image. A limited
improvement in the restorations was obtained due to the nature of the
degraded image. It was possible to restore some of the degradation
by the logarithmic estimate method. This method performed poorly,
since it was a rough approximation the degrading OTF.

The estimation of the NSR in spatial domain performed well while
the estimation in frequency domain introduced an ill-conditioned
behavior. The ill-conditioned behavior of the frequency domain
estimation can be avoided by modifying the restoration filter OTF
like we did. Except the ill-conditioned behavior, the frequency domain
estimation of the NSR performed well.

V. Conclusions and Recommendations

Conclusions

The method of spatial frequency domain inspection produces good results, if the degraded image has high frequency components, well distributed in the spatial frequency domain and a relatively small NSR so that the zeros of the degrading transfer function can be identified. The degraded image in Picture 3 met these requirements and the frequency domain method was successful. However, one must analyze the zeros and consider many possible patterns for the zero pattern of the degrading OTF. This can be done for the pictures 64x64 in size, if the degraded picture is 256x256, 512x512, or 1024x1024, recognition of the possible zero patterns may become a very difficult and time consuming task.

Image segmentation methods required that we segment the degraded image into 169 subimages. It takes about 3 hours of run-time for the segmentation method to estimate the degrading OTF using the Signal Processing Lab's Eclipse S/250 computer and the program SEGEST.FR given in Appendix B. We were not able to obtain a good estimate of the degrading OTF by the segmentation methods.

Line estimation method takes less run-time (approximately 10 minutes) and effort to estimate the degrading OTF. It was developed for the degradation due to uniform camera motion in one direction. But

may be applied to other pictures with unknown degradations. If an
improvement is obtained in the restored picture, then further steps
can be taken, such as computing an exact sinc function, or Bessel function
with the zeros of the estimated line. This method performed well in the
restoration of the degraded images that we used in this thesis.

The logarithmic estimate method performed poorly, since it was a
rough approximate to the degrading OTF.

The estimation method of the NSR in the spatial domain performed well
while the estimation in the spatial frequency introduced an ill-conditioned
behavior.

As a final statement of this discussion we can say that there is a
chance to restore images degraded by linear camera motion or out-of-
focus lens system with circular aperture with no information about the
degradation or the noise. The success in restoring the degraded images
depends upon a good estimate of the degrading OTF and the NSR. The success
in estimating these two depends upon a good modeling. The results
indicated that the logarithmic estimate could be used in the case that other
methods are not successful, since it makes a rough approximation to the
degrading OTF. The line estimation method for determining the
degrading OTF of uniform linear camera motion, and the spatial domain
and frequency domain estimation methods of the NSR could be used with
confidence to estimate the degrading OTF and the NSR respectively.

Recommendations

The depth of this research was necessarily limited. Only limited analysis and testing could be accomplished due to time constraints. Therefore, recommendations for follow-on study consists of further analysis and testing of the estimation methods.

A further study may be made on estimating the magnitude and the phase of the original image more carefully to obtain a better estimate of the degrading OTF.

In the stages of estimating the degrading OTF by segmentation method or frequency domain inspection method, the form of the degradation and necessary parameters to estimate the degrading OTF has to be obtained interactively. A study can be made to reduce the human interaction.

The case that the degradation due to both linear camera motion and out-of-focus camera was not considered. The methods described in here can be tested for this type of degradation.

If noise is not present or can be neglected, and if we take the logarithm of the Fourier transform of the degraded image, the logarithm of the degrading OTF becomes additive and the estimation of the degradation OTF from the degraded image can be considered as a noise reduction problem. The methods of noise reduction may be applied.

(Ref. 23, 24). Therefore, investigation and the implementation of them may be considered as a further study.

Appendix A

Picture 1 Original Image

Picture 2. Extruding OTF

Picture 3   Degraded (Blurred) Image

Figure 4. Display of $|G(u,v)|$

MICROCOPY RESOLUTION TEST CHART
NATIONAL BUREAU OF STANDARDS-1963

Picture 5 The Degrading OTF Obtained by Eq. (112) for d = 1/46

Picture 6 Output of the Inverse Filter [Eq. (58)]

Picture 7 Estimated OTF

Picture 8 The Exact Sinc Function

Picture 9 Output of Inverse Filter

Picture 10   Obtained by Eq. (155) for R = 0.000999

Picture 11 Obtained by Eq. (155) for R = 0.009999

A-13

Picture 12   Obtained by Eq. (155) for R = 0.099999

A-14

Picture 13   Obtained by Eq. (155) for R = 0.02

Picture 14 Degraded Image

A-16

Picture 15 Obtained by Applying Laplacian Operator [Eq. (99)] to Picture 14

A-17

Picture 16 Obtained by Eq. (46) for N=50, n=1, r=0.2033

R 183
C 227
X 258
Y 182
L 6

Picture 17   Shows the Noisy Region (Lower-left section)

A-19

Picture 18. Restored Image

Picture 19 The PSF obtained by Eq. (45)

A-21

Picture 20 The Fourier Transform of Picture 19

Picture 21 Obtained by Wiener filter with Degrading OTF of Picture 20 and the NSR of 0.172

A-23

Picture 22. Restored with the Degrading OTF Obtained by Eq. (126) and SSR = 0.172

Picture 23   Output of Wiener Filter   OTF obtained by Eq. (126) and
NSR obtained by Eq. (149) for $Sn(u,v) = 5.91$

Picture 24 Output of Wiener filter. OTF obtained by Eq. (126) and NSR by Eq. (149) for $S_n(u,v) = 2.4$

Picture 25 Output of Wiener filter. OTF obtained by Eq. (126) and NSR by Eq. (149) for $S_n(u,v)$

Picture 26 $S_n(u,v)$ estimated by Eq. (162) and Image Restored by Wiener Filter

A-28

Picture 27 Obtained by Modified Wiener Filter Eq. (151)

Picture 28 Obtained by Modified Wiener Filter Eq. (151) for
Different R Value

A-30

Picture 29 Degrading OTF estimated by Eq. (120)

Picture 30 Restored by OTF of Picture 29

A-42

Picture 31   Degrading OTF estimated by Eq. (164)

Picture 32 Restored by the OTF of Picture 31

Picture 33   Exact sinc function with the first zero of Picture 31

Picture 34 Restored by using the OTF of Picture 33

Picture 35 Sinc function obtained by Eq. (112) for d $\frac{1}{18}$

Picture 36 Restored by using the OTF of Picture 35

A-38

Picture 37 The noise image

Picture 48 Obtained by adding Picture 2 and 3 together

Picture 39   Shows the selected noisy region on the Picture 38

NOISY
REGION

A-41

Picture 40 Restored by Wiener Filter

A-42

Picture 41   Restored by Power Spectrum Equalization
Filter

Appendix B

```
C******************************************************************
C                                                                 *
C     INVFLT.FR - DG FORTRAN 5 - LT   MURAT CINCIOGLU, JULY 1985   *
C                                                                 *
C     This program implements the inverse filter  Inverse         *
C     Filter is modified to avoid the ill-conditioned behaviour    *
C     due to the zeros of the degrading OTF.                       *
C                                                                 *
C     The input files will be 2DFFT of the degraded image and      *
C     the degrading OTF  The minumum value of the degrading OTF     *
C     to avoid the zeros will also be asked. The output file       *
C     will be 2DFFT of the restored image.                         *
C                                                                 *
C     RELOAD LINE.                                                 *
C       RLDR INVFLT @FLIB@                                         *
C                                                                 *
C     COMMAND LINE                                                 *
C       INVFLT                                                     *
C                                                                 *
C                                                                 *
C******************************************************************

      COMPLEX IN1(1024), IN2(1024), OUT(1024)
      INTEGER INFLNM1(7), INFLNM2(7), OFLNM1(7)
      REAL R1, R2

C ACCEPT INPUT

      ACCEPT"ENTER BLURRED IMAGE FILE NAME --->"
      READ(11,1)INFLNM1(1)
      ACCEPT"ENTER TRANSFER FUNCTION FILE NAME--->"
      READ(11,1)INFLNM2(1)
    1 FORMAT(S13)
      ACCEPT"ENTER OUTPUT FILENAME ->"
      READ(11,1)OFLNM1(1)

      TYPE" "
      TYPE"ENTER MINUMUM VALUE TO AVOID ZEROS OF THE OTF "
      ACCEPT"                      ",R2
      CALL OPEN(1,INFLNM1,1,IER)
      CALL CHECK(IER)
      CALL OPEN(2,INFLNM2,1,IER)
      CALL CHECK(IER)

      CALL DFILW (OFLNM1,IER)
      CALL CFILW (OFLNM1,2,KER)
      CALL CHECK(KER)
      OPEN 3, OFLNM1,ATT="OR",ERR=100

  100    CONTINUE
    5    TYPE" "
         TYPE"ENTER SIZE OF FILES "
         ACCEPT" 256, 128, 64, OR 32 - ",ISIZE
```

```
C
C   TEST FOR ONLY THE ALLOWABLE SIZES
C
      IF(ISIZE.EQ.256) GO TO 6
      IF(ISIZE.EQ.128) GO TO 6
      IF(ISIZE.EQ.64) GO TO 6
      IF(ISIZE.EQ.32) GO TO 6
      GO TO 5
6     CONTINUE   ; size is okay

      IFACTOR=256/ISIZE                      ;compute scaling factor
      ITIMES=64/IFACTOR**2-1
      A=0
      DO 3 I=0,ITIMES

         CALL RDBLK(1,16*I,IN1,16,IER)
         CALL CHECK(IER)
         CALL RDBLK(2,16*I,IN2,16,IER)
         CALL CHECK(IER)

         DO 2 J=1,1024
            R1=REAL(IN2(J))**2 + AIMAG(IN2(J))**2
            R1=R1**0.5
            IF(R1.LE.R2) OUT(J)=IN1(J)
            IF (R1.GT.R2 ) OUT(J)=IN1(J)/IN2(J)
2        CONTINUE

         CALL WRBLK(3,16*I,OUT,16,IER)
         CALL CHECK(IER)

3 CONTINUE

   CALL RESET
   STOP"<7><7><7>INVFLT.FR"
   END
```

```
C******************************************************************
C                                                                 *
      WIENER.FR - DG FORTRAN 5 - LT MURAT CINCIOGLU, AUG 1986      *
C                                                                 *
C              This program implements the Wiener filter in the   *
C     Fourier domain. The inputs are the degrading OTF and the    *
C     Fourier transform of the degraded image, and the NSR. The   *
C     output will be the Fourier transform of the estimated       *
C     (restored) image.                                           *
C     RELOAD LINE:                                                *
C                                                                 *
C              RLDR WIENER @FLIB@                                 *
C                                                                 *
C     COMMAND LINE:                                               *
C                                                                 *
C              WIENER                                             *
C              Program will ask for the degrading OTF, degraded image,  *
C     and the output file names and the NSR, and the size of the files. *
C                                                                 *
C                                                                 *
C                                                                 *
C******************************************************************

      COMPLEX IN1(1024), IN2(1024), OUT(1024)
      COMPLEX H1, H2, WIENER, CSN

      INTEGER INFLNM1(7), INFLNM2(7), OFLNM1(7)

C ACCEPT INPUT
C
      ACCEPT"ENTER BLURRED IMAGE FILE NAME --->"
      READ(11,1)INFLNM1(1)
      ACCEPT"ENTER TRANSFER FUNCTION FILE NAME--->"
      READ(11,1)INFLNM2(1)
    1 FORMAT(S13)
      ACCEPT"ENTER OUTPUT FILENAME -->"
      READ(11,1)OFLNM1(1)
      TYPE" "
      ACCEPT"ENTER NOISE TO SIGNAL RATIO = ",SN
      CALL OPEN(1, INFLNM1, 1, IER)
      CALL CHECK(IER)
      CALL OPEN(2, INFLNM2, 1, IER)
      CALL CHECK(IER)

      CALL DFILW (OFLNM1, IER)
      CALL CFILW (OFLNM1, 2, KER)
      CALL CHECK(KER)
      OPEN 3, OFLNM1, ATT="OR", ERR=100

100   CONTINUE
5     TYPE" "
      TYPE"ENTER SIZE OF FILES "
      ACCEPT" 256, 128, 64, OR 32 -->", ISIZE
```

```
C
C    TEST FOR ONLY THE ALLOWABLE SIZES

     IF(ISIZE.EQ.256) GO TO 6
     IF(ISIZE.EQ.128) GO TO 6
     IF(ISIZE.EQ.64) GO TO 6
     IF(ISIZE.EQ.32) GO TO 6
     GO TO 5
6    CONTINUE    ; size is okay

     IFACTOR=256/ISIZE                    ;compute scaling factor
     ITIMES=64/IFACTOR**2-1

     DO 3 I=0,ITIMES

         CALL RDBLK(1,16*I,IN1,16,IER)
         CALL CHECK(IER)
         CALL RDBLK(2,16*I,IN2,16,IER)
         CALL CHECK(IER)

         DO 2 J=1,1024
             H1=CONJG(IN2(J))
             H2= IN2(J)*H1
             CSN=CMPLX(SN,0.0)
             WIENER= H1/( H2 + CSN )    ;Wiener Filter OTF
             OUT(J)=IN1(J)*WIENER       ; 2dfft of restored image.
2        CONTINUE

         CALL WRBLK(3,16*I,OUT,16,IER)
         CALL CHECK(IER)

3 CONTINUE

     CALL RESET
     STOP"<7><7><7>WIENER"
     END
```

B-5

```
C*********************************************************************
C                                                                    *
C      PEQFLT FR - DG FORTRAN 5 PROGRAM LT MURAT CINCIOGLU JUNE 1986 *
C                                                                    *
C      This program implements the power spectrum equalization       *
C      filter. Input files should be the degrading OTF and the       *
C      Fourier transform of the degraded image. Output file          *
C      will be the estimated (restored) image.                       *
C                                                                    *
C      RELOAD LINE:                                                   *
C        RLDR PEQFLT @FLIB@                                           *
C                                                                    *
C      COMMAND LINE:                                                  *
C        PEQFLT                                                       *
C      Program will ask for input and output file name, and the NSR. *
C                                                                    *
C                                                                    *
C*********************************************************************

        COMPLEX IN1(1024),IN2(1024),OUT(1024)
        COMPLEX H1,H2,PEQFLT,CSN

        INTEGER INFLNM1(7),INFLNM2(7),OFLNM1(7)
C
C ACCEPT INPUT
C
        ACCEPT"ENTER DEGRADED IMAGE FILE NAME -->"
        READ(11,1)INFLNM1(1)
        ACCEPT"ENTER OTF  FILE NAME            -->"
        READ(11,1)INFLNM2(1)
      1 FORMAT(S13)
        ACCEPT"ENTER OUTPUT FILE NAME          -->"
        READ(11,1)OFLNM1(1)
        TYPE" "
        ACCEPT"ENTER NOISE TO SIGNAL RATIO = ",SN
        CALL OPEN(1,INFLNM1,1,IER)
        CALL CHECK(IER)
        CALL OPEN(2,INFLNM2,1,IER)
        CALL CHECK(IER)

        CALL DFILW (OFLNM1,IER)
        CALL CFILW (OFLNM1,2,KER)
        CALL CHECK(KER)
        OPEN 3, OFLNM1,ATT="OR",ERR=100

100     CONTINUE
5       TYPE" "
        TYPE"ENTER SIZE OF FILES "
        ACCEPT" 256, 128, 64, OR 32 -->",ISIZE
```

```
C
C   TEST FOR ONLY THE ALLOWABLE SIZES
C
        IF(ISIZE.EQ.256) GO TO 6
        IF(ISIZE.EQ.128) GO TO 6
        IF(ISIZE.EQ.64) GO TO 6
        IF(ISIZE.EQ.32) GO TO 6
        GO TO 5
6       CONTINUE    ; size is okay

        IFACTOR=256/ISIZE                    ;compute scaling factor
        ITIMES=64/IFACTOR**2-1

        DO 3 I=0,ITIMES

            CALL RDBLK(1,16*I,IN1,16,IER)
            CALL CHECK(IER)
            CALL RDBLK(2,16*I,IN2,16,IER)
            CALL CHECK(IER)

            DO 2 J=1,1024
                H1=CONJG(IN2(J))
                H2= IN2(J)*H1
                CSN=CMPLX(SN,0.0)

                PEQFLT=((1.0/(H2+CSN)))**0.5

                OUT(J)=IN1(J)*PEQFLT
2           CONTINUE

            CALL WRBLK(3,16*I,OUT,16,IER)
            CALL CHECK(IER)

3 CONTINUE

    CALL RESET
    STOP"<7><7><7>PEQFLT.FR"
    END
```

B-7

```
C***************************************************************************
C                                                                          *
C         CONST.FR -    FORTRAN 5 PROGRAM LT MURAT CINCIOGLU   MAY 86       *
C                                                                          *
C         The NSR is estimated in the spatial frequency domain.            *
C         Wiener filter is then used to restore the degraded image.        *
C         Inputs are 2DFFT of the degraded image, and the noise power.     *
C         Output will be the restored image.                               *
C                                                                          *
C         RELOAD LINE:                                                     *
C           RLDR CONST @FLIB@                                              *
C                                                                          *
C         COMMAND LINE:                                                    *
C           CONST                                                          *
C         Program will ask for input and output file name, create the      *
C           output file and then ask for file size.                        *
C                                                                          *
C***************************************************************************

          COMPLEX G(1024),F(1024),HW,HBPS,NSR,DENUM,GPS,NPS,SIZE
          INTEGER INFLNM1(7),OFLNM1(7),INFLNM2(7)
          COMPLEX HB(1024)
          REAL NLEV,R,M
C
C ACCEPT INPUT
C
          ACCEPT"ENTER DEGRADED IMAGE FILE NAME -->"
          READ(11,1)INFLNM1(1)
          ACCEPT"ENTER TRANSFER FUNCTION FILE NAME -->"
          READ(11,1) INFLNM2(1)

        1 FORMAT(S13)
          ACCEPT"ENTER OUTPUT FILENAME ->"
          READ(11,1)OFLNM1(1)

          CALL OPEN(1,INFLNM1,1,IER)
          CALL CHECK(IER)

          CALL OPEN(2,INFLNM2,1,IER)
          CALL CHECK(IER)

          CALL DFILW (OFLNM1,IER)
          CALL CFILW (OFLNM1,2,KER)
          CALL CHECK(KER)
          OPEN 3, OFLNM1,ATT="OR",ERR=100

100       CONTINUE
5         TYPE" "
          TYPE"ENTER SIZE OF FILES:"
          ACCEPT" 256, 128, 64, OR 32 -->",ISIZE
          TYPE" "
          ACCEPT" ENTER MINUMUM OF DEG. OTF .....>",R
          ACCEPT" ENTER NOISE POWER .....>",NLEV
```

B-8

```
C
C   TEST FOR ONLY THE ALLOWABLE SIZES
C
      IF(ISIZE.EQ.256) GO TO 6
      IF(ISIZE.EQ.128) GO TO 6
      IF(ISIZE.EQ.64) GO TO 6
      IF(ISIZE.EQ.32) GO TO 6
      GO TO 5
6     CONTINUE    ; size is okay

      IFACTOR=256/ISIZE                        ;compute scaling factor
      ITIMES=64/IFACTOR**2-1

      SIZE=CMPLX( ISIZE**2, 0.0)
      NPS = CMPLX(NLEV,0.0)

      DO 3 I=0,ITIMES

         CALL RDBLK(1,16*I,G,16,IER)
         CALL CHECK(IER)

         CALL RDBLK(2,16*I,HB,16,IER)
         CALL CHECK(IER)

         DO 2 J=1,1024
C
C        CALCULATE NOISE TO SIGNAL RATIO (NSR)
C
         HBPS = HB(J)*CONJG( HB(J) ) *NPS

         GPS =G(J)*CONJG( G(J) )
         DENUM = GPS -NPS
         NSR =HBPS/DENUM

C        CALCULTE RESTORATION FILTER TRF
         M= HB(J)*CONJG(HB(J))
         M= SQRT(M)
         HW = CONJG(HB(J))/ ( CONJG(HB(J))*HB(J) + NSR )
         IF ( M.LT.R ) HW = CMPLX(1.0,0.0)
C
C        CALCULATE RESTORED IMAGE
C
         F(J)= G(J) * HW

2     CONTINUE

         CALL WRBLK(3,16*I,F,16,IER)
         CALL CHECK(IER)

3 CONTINUE

      CALL RESET
      STOP"<7><7><7>CONST.FR"
      END
```

```
C*********************************************************************
C                                                                    *
C        SEGEST.FR - DG FORTRAN 5 - LT MURAT CINCIOGLU, AUG 1986      *
C                                                                    *
C            This program implements the segmentation method         *
C    Its input is the degraded image  It divides the image into      *
C    square regions (subimages), each subimage is then converted to  *
C    complex representation, and Fourier transformed. Finally the     *
C    magnitude squares of the Fourier transform of each sub image are *
C    summed and averaged by the number of subimages                  *
C    LOAD LINE:                                                       *
C    RLDR SEGEST SUBIMG SVTC SFFT2 FFT2 F5PICBUF.LB @FLIB@            *
C                                                                    *
C    COMMAND LINE:                                                    *
C                                                                    *
C            SEGEST                                                   *
C            Program will ask for the I/O file names and two temporary*
C    file names, size of the subimages, and the shifting factor of the*
C    window which subimages are obtained by shifting this window.     *
C    The output file name will be the estimated power spectra.        *
C                                                                    *
C*********************************************************************

            INTEGER DIMGNM(7),TMPNM1(7),TMPNM2(7),OTFNM(7)
            INTEGER R,C,DELTHA,M,ISTR,ISTP,OPTION
            COMPLEX IN1(1024),IN2(1024),OUT(1024)
            COMPLEX CM,CMAG

            I/O CONSTANTS
            PARAMETER KTTYIN=11
            PARAMETER KTTYOUT=10
C
            ACCEPT"ENTER DEGRADED IMAGE FILE NAME :.....>"
            READ(KTTYIN,40) DIMGNM(1)
            ACCEPT"ENTER OUTPUT FILE NAME:......>"
            READ(KTTYIN,40) OTFNM(1)
            ACCEPT"ENTER TEMPORARY FILE NAME #1 .....>"
            READ(KTTYIN,40) TMPNM1(1)
            ACCEPT"ENTER TEMPORARY FILE NAME #2....>"
            READ(KTTYIN,40)TMPNM2(1)
40          FORMAT(S40)
C
C
10          TYPE"ENTER SIZE OF THE SUBIMAGES"
            ACCEPT"           128,64,32           :.....>",ISIZE
            ACCEPT"ENTER SHIFTING FACTOR :.....>",DELTHA
            IF(ISIZE.EQ.128) GO TO 20
            IF(ISIZE.EQ.64) GO TO 20
            IF(ISIZE.EQ.32) GO TO 20
            GO TO 10
20          CONTINUE
```

```
C
                CALL  DFILW(OTFNM, IER)
                CALL  CFILW(OTFNM, 2, IER)        ; 2 random file
                CALL  CHECK(IER)
                OPEN  7,  OTFNM,  ATT="OR", ERR=120
120             CONTINUE

                CALL  CFILW(TMPNM1, 2, IER)       ; initialize
                CALL  CHECK(IER)
C
                CALL  CFILW(TMPNM2, 2, IER)
                CALL  CHECK(IER)
                ISTR=1             ; starting point(1,1) for first segment
                ISTP=256-ISIZE
                DELTHA=DELTHA-1
                M=0               ; number of segments
                OPTION=1          ; 2D forward Fourier transform

                IFACTOR=256/ISIZE
                ITIMES=64/IFACTOR**2-1

                DO 2 I=0, ITIMES
                DO 3 J=1, 1024
                        OUT(J)=CMPLX(0. 0, 0. 0)
3               CONTINUE

                CALL  WRBLK(7, 16*I, OUT, 16, IER)
                CALL  CHECK(IER)
2               CONTINUE

                DO 25 R=1, ISTP, DELTHA

                DO 35 C=1, ISTP, DELTHA
                M=M+1

99              CALL  SUBIMG(DIMGNM, TMPNM1, ISIZE, C, R)         ; segmentation

                CALL  SVTC(ISIZE, TMPNM1, TMPNM2)    ; convert to complex
                CALL  SFFT2(TMPNM2, OPTION)          ; 2D-forward FFT
                OPEN  2, TMPNM2,  ATT="OR", ERR=101
                OPEN  7, OTFNM,  ATT="ORR", ERR=101
101             CONTINUE

                DO 55 I=0, ITIMES
                CALL  RDBLK(2, 16*I, IN1, 16, IER)
                CALL  CHECK(IER)

                CALL  RDBLK(7, 16*I, IN2, 16, IER)
                CALL  CHECK(IER)
```

```
                        DO 50 J=1,1024

                        OUT(J)=IN2(J)  +  IN1(J)*CONJG(IN1(J))

         50             CONTINUE
                        CALL WRBLK(7,16*I,OUT,IER)
                        CALL CHECK(IER)
         55             CONTINUE
                        TYPE"SEGMENT #",M
         35             CONTINUE


         25             CONTINUE
         109            CM=CMPLX(FLOAT(M),0.0)
                        DO 77 I=0,ITIMES
                        CALL RDBLK(7,16*I,OUT,IER)
                        CALL CHECK(IER)
                        DO 87 J=1,1024

                        OUT(J)=OUT(J)/CM          ;average by M

         87             CONTINUE
                        CALL WRBLK(7,16*I,OUT,IER)
                        CALL CHECK(IER)
         77             CONTINUE
                        TYPE"NUMBER OF SEGMENTS=",M
                        CALL RESET
                        STOP"<7><7><7>SEGEST.FR"
                        END
```

```
C*********************************************************************
C                                                                    *
       SEGEST2.FR -- DG FORTRAN 5 - LT MURAT CINCIOGLU, AUG 1986      *
C                                                                    *
C              This program implements the segmentation method.      *
C       Its input is the degraded image. It divides the degraded image *
C       into M subimages. The magnitude of the Fourier transform of each *
C       subimage is then multipled and 1/M power of the result is    *
C       calculated to estimate the magnitude of the degrading OTF.   *
C       RELOAD LINE:                                                  *
C                                                                    *
C       RLDR SEGEST2 SVTC SFFT2 FFT2 UNP F5PICBUF.LB @FLIB@           *
C                                                                    *
C       COMMAND LINE:                                                 *
C                                                                    *
C              SEGEST2                                                *
C              Program will ask for the I/O and two temporary        *
C       file names, the size of the subimages and the shifting factor. *
C       The output will be the magnitude of the estimated degrading OTF. *
C                                                                    *
C                                                                    *
C*********************************************************************

              INTEGER DIMGNM(7),TMPNM1(7),TMPNM2(7),OTFNM(7)
              INTEGER R,C,DELTHA,M,ISTR,ISTP,OPTION
              COMPLEX IN1(1024),IN2(1024),OUT(1024)
              REAL R1,R2,RM
              I/O CONSTANTS
              PARAMETER KTTYIN=11
              PARAMETER KTTYOUT=10
C
              ACCEPT"ENTER DEGRADED IMAGE FILE NAME :....>"
              READ(KTTYIN,40) DIMGNM(1)
              ACCEPT"ENTER OUTPUT FILE NAME:.....>"
              READ(KTTYIN,40) OTFNM(1)
              ACCEPT"ENTER TEMPORARY FILE NAME #1 ....>"
              READ(KTTYIN,40) TMPNM1(1)
              ACCEPT"ENTER TEMPORARY FILE NAME #2....>"
              READ(KTTYIN,40)TMPNM2(1)
40            FORMAT(S40)
C
C
10            TYPE"ENTER SIZE OF THE SUBIMAGES"
              ACCEPT"        128,64,32          :....>",ISIZE
              ACCEPT"ENTER SHIFTING FACTOR :....>",DELTHA
              IF(ISIZE.EQ.128) GO TO 20
              IF(ISIZE.EQ.64) GO TO 20
              IF(ISIZE.EQ.32) GO TO 20
              GO TO 10
20            CONTINUE
```

B-13

```
C
                    CALL DFILW(OTFNM, IER)
                    CALL CFILW(OTFNM, 2, IER)       ; 2 random file
                    CALL CHECK(IER)
                    OPEN 7, OTFNM, ATT="OR", ERR=120
    120             CONTINUE

                    CALL CFILW(TMPNM1, 2, IER)      ; initialize
                    CALL CHECK(IER)
C
                    CALL CFILW(TMPNM2, 2, IER)
                    CALL CHECK(IER)
                    ISTR=1                 ; starting point(1,1) for first segment
                    ISTP=256-ISIZE
                    DELTHA=DELTHA-1
                    M=0                    ;number of segments
                    OPTION=1               ; 2D forward Fourier transform

                    IFACTOR=256/ISIZE
                    ITIMES=64/IFACTOR**2-1

                    DO 2 I=0, ITIMES
                    DO 3 J=1, 1024
                            OUT(J)=CMPLX(1.0, 0.0)    ;initialize
    3               CONTINUE

                    CALL WRBLK(7, 16*I, OUT, 16, IER)
                    CALL CHECK(IER)
    2               CONTINUE

                    DO 25 R=1, ISTP, DELTHA

                    DO 35 C=1, ISTP, DELTHA
                    M=M+1

    99              CALL SUBIMG(DIMGNM, TMPNM1, ISIZE, C, R)         ; segmentation

                    CALL SVTC(ISIZE, TMPNM1, TMPNM2)  ; convert to complex
                    CALL SFFT2(TMPNM2, OPTION)        ; 2D-forward FFT
                    OPEN 2, TMPNM2, ATT="OR", ERR=101
                    OPEN 7, OTFNM, ATT="ORR", ERR=101
    101             CONTINUE

                    DO 55 I=0, ITIMES
                    CALL RDBLK(2, 16*I, IN1, 16, IER)
                    CALL CHECK(IER)

                    CALL RDBLK(7, 16*I, IN2, 16, IER)
                    CALL CHECK(IER)
```

```fortran
              DO 50 J=1,1024

              R1=( REAL(IN1(J)) )**2  + ( AIMAG(IN1(J)) )**2
              R2=( REAL(IN2(J)) )**2  + ( AIMAG(IN2(J)) )**2
              R1= R1**0.5
              R2= R2**0.5
              RR= R1*R2
              OUT(J)=CMPLX(RR,0.0)

50            CONTINUE
              CALL WRBLK(7,16*I,OUT,IER)
              CALL CHECK(IER)
55            CONTINUE
              TYPE"SEGMENT #",M
35            CONTINUE


25            CONTINUE

109           RM=1.0/(FLOAT(M))

              DO 77 I=0,ITIMES

              CALL RDBLK(7,16*I,OUT,IER)
              CALL CHECK(IER)
              DO 87 J=1,1024
              RR=( REAL(OUT(J)) )** RM
              OUT(J)=CMPLX(RR,0.0)

87            CONTINUE
              CALL WRBLK(7,16*I,OUT,IER)
              CALL CHECK(IER)
77            CONTINUE

              TYPE"NUMBER OF SEGMENTS=",M
              CALL RESET
              STOP"<7><7><7>SEGEST2.FR"
              END
```

```
C****************************************************************************
C                                                                          *
        SEGEST3.FR   DG FORTRAN 5 - LT MURAT CINCIOGLU, AUG 1986           *
C                                                                          *
C              This program obtains implements the segmentation            *
C      method. Obtains an estimate of the complex logarithm of degrading   *
C      OTF by avereging the complex logarithm of the Fourier transform of  *
C      subimages.                                                          *
C                                                                          *
C      RELOAD LINE:                                                        *
C                                                                          *
C      RLDR SEGEST3 SUBIMG SVTC UNP SFFT2 F5PICBUF.LB @FLIB@               *
C                                                                          *
C      COMMAND LINE:                                                       *
C                                                                          *
C              SEGEST3                                                     *
C              Program will ask for I/O file and two temporary file names  *
C      and for the shifting foctor, and the size of the subimages.         *
C                                                                          *
C                                                                          *
C                                                                          *
C****************************************************************************


              INTEGER DIMGNM(7),TMPNM1(7),TMPNM2(7),OTFNM(7)
              INTEGER R,C,DELTHA,M,ISTR,ISTP,OPTION
              COMPLEX IN1(1024),IN2(1024),OUT(1024)
              COMPLEX CM
              REAL ROUT,IOUT,RR,II

C             I/O CONSTANTS
              PARAMETER KTTYIN=11
              PARAMETER KTTYOUT=10

C
              ACCEPT"ENTER DEGRADED IMAGE FILE NAME :.....>"
              READ(KTTYIN,40) DIMGNM(1)
              ACCEPT"ENTER OUTPUT FILE NAME:.....>"
              READ(KTTYIN,40) OTFNM(1)
              ACCEPT"ENTER TEMPORARY FILE NAME #1 ....>"
              READ(KTTYIN,40) TMPNM1(1)
              ACCEPT"ENTER TEMPORARY FILE NAME #2....>"
              READ(KTTYIN,40)TMPNM2(1)
40            FORMAT(S40)
C
C
10            TYPE"ENTER SIZE OF THE SUBIMAGES"
              ACCEPT"        128,64,32          .....>",ISIZE
              ACCEPT"ENTER SHIFTING FACTOR .....>",DELTHA
              IF(ISIZE.EQ.128) GO TO 20
              IF(ISIZE.EQ.64) GO TO 20
              IF(ISIZE.EQ.32) GO TO 20
              GO TO 10
20            CONTINUE
```

```
C
                    CALL DFILW(OTFNM,IER)
                    CALL CFILW(OTFNM,2,IER)      ; 2 random file
                    CALL CHECK(IER)
                    OPEN 7, OTFNM, ATT="OR",ERR=120
  120               CONTINUE

                    CALL CFILW(TMPNM1,2,IER)      ; initial
                    CALL CHECK(IER)
C
                    CALL CFILW(TMPNM2,2,IER)
                    CALL CHECK(IER)
                    ISTR=1              ; starting point(1,1) for first segment
                    ISTP=256-ISIZE
                    DELTHA=DELTHA-1
                    M=0              ;number of segments
                    OPTION=1              ; 2D forward Fourier transform

                    IFACTOR=256/ISIZE
                    ITIMES=64/IFACTOR**2-1

                    DO 2 I=0,ITIMES
                    DO 3 J=1,1024
                            OUT(J)=CMPLX(0.0,0.0)
  3                 CONTINUE

                    CALL WRBLK(7,16*I,OUT,16,IER)
                    CALL CHECK(IER)
  2                 CONTINUE

                    DO 25 R=1,ISTP,DELTHA

                    DO 35 C=1,ISTP,DELTHA
                    M=M+1

  99                CALL SUBIMG(DIMGNM,TMPNM1,ISIZE,C,R)          ;segmentation

                    CALL SVTC(ISIZE,TMPNM1,TMPNM2)  ; convert to complex
                    CALL SFFT2(TMPNM2,OPTION)          ; 2D-forward FFT
                    OPEN 2,TMPNM2, ATT="OR",ERR=101
                    OPEN 7,OTFNM, ATT="ORR",ERR=101
  101               CONTINUE

                    DO 55 I=0,ITIMES
                    CALL RDBLK(2,16*I,IN1,16,IER)
                    CALL CHECK(IER)

                    CALL RDBLK(7,16*I,IN2,16,IER)
                    CALL CHECK(IER)
```

```
                        DO 50 J=1,1024

                        OUT(J)=IN2(J) + CLOG(IN1(J))

50                      CONTINUE
                        CALL WRBLK(7,16*I,OUT,IER)
                        CALL CHECK(IER)
55                      CONTINUE
                        TYPE"SEGMENT #",M
35                      CONTINUE


25                      CONTINUE
109                     CM=CMPLX(FLOAT(M),0.0)
                        DO 77 I=0,ITIMES
                        CALL RDBLK(7,16*I,OUT,IER)
                        CALL CHECK(IER)
                        DO 87 J=1,1024

                        OUT(J)=OUT(J)/CM          ;average by M
87                      CONTINUE
                        CALL WRBLK(7,16*I,OUT,IER)
                        CALL CHECK(IER)
77                      CONTINUE
                        TYPE"NUMBER OF SEGMENTS=",M
                        CALL RESET
                        STOP"<7><7><7>SEGES13.FR"
                        END
```

```
C********************************************************************
C                                                                   *
C                                                                   *
C           MTRF.FR --- DG FORTRAN 5 - LT MURAT CINCIOGLU, AUG 1986 *
C                                                                   *
C               This program obtains a degrading OTF for the motion *
C       blur in the horizontal direction. The degrading OTF of the  *
C       motion blur in vertical direction can be obtained by tranforming *
C       the output file.                                            *
C                                                                   *
C       RELOAD LINE:                                                *
C                                                                   *
C               RLDR MTRF    @FLIB@                                 *
C                                                                   *
C       COMMAND LINE:                                               *
C                                                                   *
C               MTRF                                                *
C               Program will ask for the degrading OTF file name,   *
C       total exposure time (T), and total displacement distance (d), *
C       and the size of the output file.                            *
C                                                                   *
C                                                                   *
C********************************************************************


              COMPLEX TRF(256)
              PARAMETER KTTYIN=11,KTTYOUT=10, PI=3.1415927
              REAL  R1,R2,T,d,R,RO,X
              INTEGER OFLNM(7)

              WRITE(KTTYOUT,12)
12            FORMAT("ENTER FILE NAME ........>",Z)
              READ(KTTYIN,14) OFLNM(1)
14            FORMAT( S39 )

              TYPE" "
              ACCEPT"ENTER EXPOSURE TIME .......>",T
              TYPE" "
              ACCEPT"ENTER TOTAL DIPLACEMENT ("d")...>",d

              CALL DFILW(OFLNM,IER)
              CALL CFILW(OFLNM,2,KER)
              CALL CHECK( KER )
              CALL FOPEN(2,OFLNM)

C             CALCULATE TRANSFER FUNCTION

              DO 20 U=1,256
                 X= U-128.0
                 RO= PI*X*d
                 IF( X.EQ.0.0 ) R=T
                 IF( X.NE.0.0 ) R=( T*SIN( RO ) )/( RO )
                 R1= R*COS( RO )
                 R2= -R*SIN( RO )
                 TRF(U) = CMPLX( R1,R2 )
20            CONTINUE
```

```
            TYPE"WRITING TRANSFER FUNCTION"
            DO 30 I=1,256
                    DO 40 J=1,256
                      WRITE(2) TRF(J)
40                  CONTINUE
              IF( MOD(I,50).EQ.0) TYPE"DONE",I
30          CONTINUE
            CLOSE 2

            STOP"<7><7><7>MTRF.FR"
            END
```

```
C******************************************************************************
C                                                                            *
C      DPSF.FR- DG FORTRAN 5 - LT MURAT CINCIOGLU, MAY 1986                   *
C                                                                            *
C      This program calculates two-dimensioanal point spread function*
C      for an out-of-focus camera with circular aperture in the              *
C      normalized coordinates.                                               *
C                                                                            *
C                                                                            *
C      RELOAD LINE:                                                          *
C        RLDR DPSF @FLIB@                                                     *
C                                                                            *
C      COMMAND LINE:                                                         *
C        DPSF                                                                *
C      Program will ask for an output file name, create the                  *
C        output file and then ask for file size, the radius of the          *
C        defocusing error.                                                   *
C******************************************************************************

       COMPLEX OUT(1024)
       INTEGER OFLNM1(7)
       REAL R,RD,VAL,VAL2
       REAL X,Y, RSIZE,OR
       PARAMETER PI=3.1415927


C
C  ACCEPT INPUT
C
     1 FORMAT(S13)
       ACCEPT"ENTER OUTPUT FILENAME -:"
       READ(11,1)OFLNM1(1)

       CALL DFILW (OFLNM1,IER)
       CALL CFILW (OFLNM1,2,KER)
       CALL CHECK(KER)
       OPEN 3, OFLNM1,ATT="OR",ERR=100

100    CONTINUE
5      TYPE" "
       TYPE"ENTER SIZE OF FILES:"
       ACCEPT" 256, 128, 64, OR 32 --:",ISIZE
       ACCEPT"RADIUS OF DEFOCUSING --:",R


C
C   TEST FOR ONLY THE ALLOWABLE SIZES
C
       IF(ISIZE.EQ.256) GO TO 6
       IF(ISIZE.EQ.128) GO TO 6
       IF(ISIZE.EQ.64) GO TO 6
       IF(ISIZE.EQ.32) GO TO 6
       GO TO 5
6      CONTINUE    ; size is okay
       RSIZE = ISIZE        ; type conversion
```

```
      OR = RSIZE/2.0         ; origin

      DO 3 I=1,ISIZE

         DO 2 J=1,ISIZE
              X = J
              X =(X - OR)/OR; translate to center

              Y = I                 .
              Y = (Y - OR)/OR
              RD= X**2 + Y**2
              VAL2= PI*RD
              RD= SQRT(RD)
              VAL= 0.0
              IF( RD.LE.R ) VAL = 1.0/VAL2
          OUT(J) = CMPLX(VAL,0.0)
          WRITE(3) OUT(J)
2      CONTINUE
          IF( MOD(I,50).EQ.0) TYPE" DONE ...>",I
3 CONTINUE

   CALL RESET
   STOP"<7><7><7>DPSF.FR"
   END
```

```
C***************************************************************************
C                                                                         *
         BESSEL.FR - DG FORTRAN 5 - LT MURAT CINCIOGLU, AUG 1986           *
                                                                          *
C           This program obtains a degrading OTF for defocused             *
C        camera with circular aperture.                                    *
C                                                                          *
C        RELOAD LINE:                                                      *
C                                                                          *
C            RLDR BESSEL @FLIB@                                            *
C                                                                          *
C        COMMAND LINE:                                                     *
C                                                                          *
C            BESSEL                                                        *
C            Program will ask for the degrading OTF file name,            *
C        radii of the first minima, number of terms to approximate        *
C        the Bessel function of first kind with order one, and the         *
C        size of the output file.                                          *
C                                                                          *
C***************************************************************************

               COMPLEX TRF(256)
               PARAMETER KTTYIN=11,KTTYOUT=10
               REAL   C(256) ,X,R,F,U,V,OR,C2(256),WX,WY,SIZE,APRX,J1,J,N,K
               INTEGER OFLNM(7)
               REAL K2 ,A
C
               WRITE(KTTYOUT,12)
12             FORMAT("ENTER FILE NAME  FOR THE TRANSFER FUNCTION   >",Z)
               READ(KTTYIN,14) OFLNM(1)
14             FORMAT( S39 )


               TY E" "
               TYPE"ENTER DEFOCUSING ERROR( Radii of the first minima)"
               ACCEPT"                                       ...>",R
               TYPE" "
               TYPE"HOW MANY TERMS SHOULD BE CALCULATED FOR THE BESSEL FUNC."
               ACCEPT"                                ........>",APRX

               ACCEPT"ENTER SIZE OF THE OUTPUT FILE            ........>",SIZE


               CALL DFILW(OFLNM,IER)
               CALL CFILW(OFLNM,2,KER)
               CALL CHECK(KER)
               CALL FOPEN(2,OFLNM)
```

```
C               CALCULATE TRANSFER FUNCTION
                OR=SIZE/2.0
                DO 50 I=1,APRX
                C(I)=1.0
                C2(I)=1.0
50              CONTINUE

                  DO 100 I=1, APRX
                   X= I
                   DO 200 J=1.0,X
                       C(I)=C(I)*J
                       C2(I)=C2(I)*J
200                 CONTINUE
                       C2(I)=C2(I)*(X+1.0)
100             CONTINUE
                N= APRX
                DO 20 WY=1.0,SIZE
                DO 30 WX=1.0,SIZE

                  V=(WY-OR)/OR ; normalized coord.
                  U=(WX-OR)/OR    ;translate org.to the cntr.of the file
                  F=( U**2+V**2 ) **0.5
                  X= 2.0*R*F
                  IF(X.EQ.0.0) GO TO 310
                  J1=X/2.0
                  A=1.0
                  DO 300 I=1,APRX
                     K= I                    ; type conversion
                     K2=1.0+2.0*K
                      IF(MOD(I,2).EQ.0) A=-1.0
                   J1= J1-A* ((X/2.0)**K2 ) /(C(I)*C2(I))
300             CONTINUE

310             IF(X.EQ.0.0) TRF(WX)=CMPLX(1.0,0.0)
                IF(X.EQ.0.0) GO TO 19
                J1=J1/(R*F)
                IF(X.NE.0.0) TRF(WX)=CMPLX(J1,0.0)
19              WRITE(2) TRF(WX)
30              CONTINUE
                IF(MOD(WY,OR).EQ.0.0) TYPE"DONE...:",WY
20              CONTINUE
                CLOSE 2
                STOP"<7><7><7>BESSEL FR"
                END
```

```
C*********************************************************************
C                                                                    *
C        LEST FR --- DG FORTRAN 5 - LT MURAT CINCIOGLU, AUG 1986      *
C                                                                    *
C            This program implements the line estimation method.     *
C    It estimates a line in the vertical direction and duplicates    *
C    this line to obtain an output file which is identical in size   *
C    to the input file.                                              *
C                                                                    *
C    RELOAD LINE.                                                     *
C                                                                    *
C            RLDR LEST    @FLIB@                                      *
C                                                                    *
C    COMMAND LINE:                                                    *
C                                                                    *
C            LEST                                                     *
C            Program will ask for the input file size, and input/    *
C    output file names                                               *
C                                                                    *
C                                                                    *
C                                                                    *
C*********************************************************************


              COMPLEX IN1(256),OUT1(256),OUT(256)
              COMPLEX NB,EST
              INTEGER INFLNM(7),OFLNM(7),JMP,K,M,N,STEP,WINDOW,KSIZE

C             ACCEPT INPUT
              TYPE"INPUT FILE SHOULD BE FOURIER TRANSFORM OF "
              TYPE"THE DEGRADED IMAGE..."
              TYPE" "
              WRITE(10,12)
12            FORMAT("ENTER INPUT FILE NAME = -->",Z)
              READ(11,14) INFLNM(1)
14            FORMAT(S39)

              WRITE(10,16)
16            FORMAT("ENTER OUTPUT FILE NAME = -->",Z)
              READ(11,14) OFLNM(1)

              TYPE" ENTER SIZE OF INPUT FILE :"
              ACCEPT"32,64,128,256            -->",ISIZE
              TYPE" "
C             TYPE" ENTER WINDOW SIZE  "
C             ACCEPT"1,2,4,8,16,32,64,128    >",WINDOW
C
C
              WINDOW = 1
```

```
                CALL OPEN(1,INFLNM,1,IER)
                CALL CHECK(IER)
                CALL DFILW(OFLNM,IER)
                CALL CFILW(OFLNM,2,KER)
                CALL CHECK(KER)
                CALL FOPEN(2,OFLNM)
6               CONTINUE

                REWIND 1
                REWIND 2

C
                KSIZE= ISIZE-3

                STEP= ISIZE/WINDOW        ; number of windows
                JMP= STEP-1
                NR= CMPLX(STEP,0.0)

        DO 100 I=1,ISIZE
           DO 200 J=1,ISIZE
                READ(1) IN1(J)                ;READ ONE ROW AT ATIME
200           CONTINUE
           DO 300 K=1,WINDOW
                EST= CMPLX(0.0,0.0)
                DO 400 J=0,JMP
                   KW=K+J*WINDOW
                   EST=EST+CLOG( IN1(KW) )
400             CONTINUE
                OUT1(K)=EST/NR
300           CONTINUE

C       ENLARGE THE PROCESSED WINDOW INTO "ISIZE"
           M=0
           DO 500 J=1,KSIZE,STEP
                M=M+1
                DO 600 N=0,JMP
                   OUT(J+N)=OUT1(M)
600             CONTINUE
500           CONTINUE
           DO 700 J=1,ISIZE
                WRITE(2) OUT(J)
700           CONTINUE
           IF(MOD(I,64).EQ.0)TYPE" DONE  ",I
100     CONTINUE
        CLOSE1
        CLOSE2
        STOP<7><7><7><7>LEST FR"
        END
```

```
C************************************************************************
C                                                                      *
C     LOGTRF.FR DG FORTRAN 5- LT MURAT CINCIOGLU,  JUNE 85             *
C                                                                      *
C      This program estimates degrading OTF from degraded             *
C       image and calculates Wiener filter transfer function          *
C       for the restoration filter.                                   *
C                                                                      *
C      LOGTRF estimates the OTF by taking complex logarithm of        *
C      Fourier transform of the degraded image and deviding by        *
C      total number of pixels in a line.                              *
C                                                                      *
C      RELOAD LINE:                                                    *
C         RLDR LOGTRF @FLIB@                                           *
C                                                                      *
C      COMMAND LINE:                                                   *
C         LOGTRF                                                       *
C      Program will ask for input and output file name, create the    *
C      output file and then ask for file size.                        *
C      Input file name should be Fourier transform of the degraded    *
C      image. Noise-to-Signal ratio is also asked for Wiener filter.  *
C      Noise-to-signal raio is assumed to be constant.                *
C                                                                      *
C************************************************************************

      COMPLEX HB(1024),  G(1024),HW(1024),OUT(1024)
      INTEGER INFLNM1(7),  OFLNM1(7)
      REAL NS
C
C ACCEPT INPUT
C
      ACCEPT"ENTER DEGRADED IMAGE FILE NAME ....>"
      READ(11,1)INFLNM1(1)
    1 FORMAT(S13)
      ACCEPT"ENTER OUTPUT FILENAME ->"
      READ(11,1)OFLNM1(1)

      CALL OPEN(1,INFLNM1,1,IER)
      CALL CHECK(IER)

      CALL DFILW (OFLNM1,IER)
      CALL CFILW (OFLNM1,2,KER)
      CALL CHECK(KER)
      OPEN 3,  OFLNM1,ATT="OR",ERR=100

100   CONTINUE
5     TYPE" "
      TYPE"ENTER SIZE OF FILES "
      ACCEPT" 256,  128,  64,  OR 32 -->",ISIZE
```

```fortran
C
C   TEST FOR ONLY THE ALLOWABLE SIZES
C
      IF(ISIZE.EQ.256) GO TO 6
      IF(ISIZE.EQ.128) GO TO 6
      IF(ISIZE.EQ.64) GO TO 6
      IF(ISIZE.EQ.32) GO TO 6
      GO TO 5
6     CONTINUE   ; size is okay

      IFACTOR=256/ISIZE                  ;compute scaling factor
      ITIMES=64/IFACTOR**2-1

      SIZE = CMPLX(ISIZE**2,0.0)
      CNS = CMPLX(NS,0.0)

      DO 3 I=0,ITIMES

         CALL RDBLK(1,16*I,G,16,IER)
         CALL CHECK(IER)

         DO 2 J=1,1024

            HB(J) = CLOG( G(J) ) / SIZE ;   estimated OTF of degradi

            HW(J) = CONJG( HB(J) )/( HB(J)*CONJG(HB(J)) + CNS ) ; W

            OUT(J)= HW(J)*G(J)

2     CONTINUE

         CALL WRBLK(3,16*I,OUT,16,IER)
         CALL CHECK(IER)

3 CONTINUE

   CALL RESET
   STOP"<7><7><7>LOGTRF"
   END

                     .
```

```
C*****************************************************************************
C                                                                           *
C CEPST.FR -- DG FORTRAN 5 PROGRAM LT MURAT CINCIOGLU 5 JUNE 1986           *
C                                                                           *
C          This program computes the cepstrum of the degraded image        *
C          The input file should be the Fourier transform of the           *
C          degraded image.                                                  *
C                                                                           *
C      RELOAD LINE:                                                         *
C        RLDR CEPST SFFT2 @FLIB@                                            *
C                                                                           *
C      COMMAND LINE:                                                        *
C        CEPST.FR                                                           *
C      Program will ask for input and output file name, create the         *
C        output file and then ask for file size.                           *
C                                                                           *
C*****************************************************************************

        COMPLEX IN1(1024),OUT(1024)
        COMPLEX CEP
        REAL AMP
        INTEGER INFLNM1(7),OFLNM1(7)
C ACCEPT INPUT
C
        ACCEPT"ENTER INPUT FILENAME #1 ->"
        READ(11,1)INFLNM1(1)
      1 FORMAT(S13)
        ACCEPT"ENTER OUTPUT FILENAME ->"
        READ(11,1)OFLNM1(1)

        CALL OPEN(1,INFLNM1,1,IER)
        CALL CHECK(IER)
        CALL DFILW (OFLNM1,IER)
        CALL CFILW (OFLNM1,2,KER)
        CALL CHECK(KER)
        OPEN 8, OFLNM1,ATT="OR",ERR=100

100     CONTINUE
5       TYPE" "
        TYPE"ENTER SIZE OF FILES ."
        ACCEPT" 256, 128, 64, OR 32 -->",ISIZE
C
C   TEST FOR ONLY THE ALLOWABLE SIZES
C
        IF(ISIZE.EQ.256) GO TO 6
        IF(ISIZE.EQ.128) GO TO 6
        IF(ISIZE.EQ.64) GO TO 6
        IF(ISIZE.EQ.32) GO TO 6
        GO TO 5
6       CONTINUE   ; size is okay
```

```
        DO 2 J=1,ISIZE


              DO 4 K=1,ISIZE
              READ(1) IN1(K)
              AMP= REAL(IN1(K)) **2 + AIMAG(IN1(K))**2
              AMP=SQRT(AMP)
              AMP=LOG(AMP)
C             IF(AMP.NE.0.0) AMP= LOG(AMP)
C             IF(AMP.EQ.0.0) AMP=0.0
              CEP=CMPLX(AMP,0.0)
              OUT(K)=CEP
                 WRITE(8) OUT(K)
4             CONTINUE
2       CONTINUE
      CLOSE 8
        CALL SFFT2(OFLNM1,1)


      STOP"<7><7><7>CEPST.FR"
      END
```

```
C*****************************************************************************
C
C           LAP.FR  --  DG FORTRAN 5   LT MURAT CINCIOGLU, AUG 1986
C
C               This program applies the Laplacian operator to
C       the input image.
C
C       RELOAD LINE:
C
C               RLDR LAP F5PICBUF.LB @FLIB@
C
C       COMMAND LINE:
C
C               LAP
C
C
C*****************************************************************************


        PARAMETER NBUFSZ=300, KTTYOUT=10, KTTYIN=11
        PARAMETER NCOLSMAX=256
        INTEGER IBUF(NBUFSZ)
        INTEGER IARRAY(NCOLSMAX,3), IARRAY2(NCOLSMAX), INAME(20)


C       INITIALIZE INPUT AND OUTPUT BUFFERS AND READ IN INPUT PICTURE

10      WRITE (KTTYOUT,996)
996     FORMAT("INPUT PICTURE FILE NAME = ",Z)
        READ (KTTYIN,997) INAME(1)
997     FORMAT(S39)
        CALL PICFMT(IBUF,INAME,IFLG)
        CALL GFMT(IBUF,NROWS,NCOLS,NBITS,IMODE)
        IF (IMODE.EQ.3) GO TO 10
        IF ((NROWS.LT.3).OR.(NCOLS.LT.3)) GO TO 10
        IF (NCOLS.GT.NCOLSMAX) GO TO 10
        IF (NBITS.GT.11) GO TO 10   , to preclude integer overflow
        CALL MAKB(IBUF)
        CALL PICIN(IBUF,INAME,IFLG)

C       INITIALIZE CONVOLUTION PROCESS

        CALL GROW(IBUF,1,1,NCOLS,IARRAY(1,1))
        CALL GROW(IBUF,2,1,NCOLS,IARRAY(1,2))
        I1=0
        I2=1
        I3=2
        NR1=NROWS-1
        NC1=NCOLS-1
        IARRAY2(1)=0
        IARRAY2(NCOLS)=0
```

```
C       PERFORM CONVOLUTION A ROW AT A TIME

        DO 200 I=2,NR1
        IF (MOD(I,10).EQ.0) WRITE(KTTYOUT,998) I
998     FORMAT("ROW = ",I3)

        I1=MOD(I1,3)+1
        I2=MOD(I2,3)+1
        I3=MOD(I3,3)+1

        CALL GROW(IBUF,I+1,1,NCOLS,IARRAY(1,I3))

        DO 100 J=2,NC1
        IVAL=       IARRAY(J-1,I1)*0 -IARRAY(J,I1)+IARRAY(J+1,I1) *0
        IVAL=IVAL-IARRAY(J-1,I2)+IARRAY(J,I2)*5-IARRAY(J+1,I2)
        IVAL=IVAL+IARRAY(J-1,I3)*0-IARRAY(J,I3)+IARRAY(J+1,I3)*0
        if(IVAL.LT.0) IVAL=(-1)*IVAL
        if(IVAL.GT.15) IVAL=15
        IARRAY2(J)= IVAL          , (laplacian of image)
100     CONTINUE
        CALL PROW(IBUF,I,1,NCOLS,IARRAY2)
200     CONTINUE

C       OUTPUT RESULT AND RELEASE BUFFERS

        WRITE (KTTYOUT,999)
999     FORMAT("OUTPUT PICTURE FILE NAME = ",Z)
        READ (KTTYIN,997) INAME(1)
        CALL PICOUT(IBUF,INAME,IFLG)
        CALL RELB(IBUF)
        STOP "<7><7><7>LAP.FR"
        END
```

B-32

```
C***********************************************************************
C                                                                      *
C       ADV.FR   --   DG FORTRAN 5 - LT MURAT CINCIOGLU, AUG 1986      *
C                                                                      *
C               This program adds two integer picture files to        *
C       obtain the output file.                                        *
C                                                                      *
C       RELOAD LINE:                                                   *
C                                                                      *
C               RLDR ADV F5PICBUF.LB @FLIB@                            *
C                                                                      *
C       COMMAND LINE:                                                  *
C                                                                      *
C               ADV                                                    *
C                                                                      *
C                                                                      *
C                                                                      *
C***********************************************************************


                PARAMETER KTTYIN=11,KTTYOUT=10,NBUFSZ=300
                PARAMETER MAXCOL=256,MAXROW=256
                INTEGER IBUF1(NBUFSZ),IBUF2(NBUFSZ),IBUF(NBUFSZ)
                INTEGER INAME1(7),INAME2(7),ONAME(7)
                INTEGER IARRAY1(MAXCOL),IARRAY2(MAXCOL),IARRAY(MAXCOL)
C
C
                WRITE(KTTYOUT,990)
990             FORMAT(1X,"ENTER PICTURE FILE NAME #1 :...>",Z)
                READ(KTTYIN,991) INAME1(1)
991             FORMAT(S39)
C
                WRITE(KTTYOUT,993)
993             FORMAT(1X,"ENTER PICTURE FILENAME #2 :....>",Z)
                READ(KTTYIN,991) INAME2(1)
C
                WRITE(KTTYOUT,992)
992             FORMAT(1X,"ENTER OUTPUT FILE NAME  -->",Z)
                READ(KTTYIN,991) ONAME(1)
C
C
                CALL PICFMT(IBUF1,INAME1,IHDR)
                CALL MAKB(IBUF1)
                CALL PICIN(IBUF1,INAME1,IHDR)
                CALL GFMT(IBUF1,NROWS,NCOLS,NBITS,IMODE)
C
C
                CALL PICFMT(IBUF2,INAME2,IHDR)
                CALL MAKB(IBUF2)
                CALL PICIN(IBUF2,INAME2,IHDR)
                CALL GFMT(IBUF2,NROWS,NCOLS,NBITS,IMODE)
                CALL PFMT(IBUF,NROWS,NCOLS,NBITS,IMODE)
                CALL MAKB(IBUF)
```

```
                DO 500 I=1,NROWS
                CALL GROW(IBUF1,I,1,NCOLS,IARRAY1)     ; get rows
                CALL GROW(IBUF2,I,1,NCOLS,IARRAY2)
                DO 600 J=1,256
                   IVAL =IARRAY1(J) + IARRAY2(J)   ; add rows
                   IF(IVAL.LT.0) IVAL =-1*IVAL
                   IF(IVAL.GT.15) IVAL=15
                   IARRAY(J)=IVAL
600             CONTINUE

                IF(MOD(I,64).EQ.0) TYPE"DONE ...:",I  ; report to keyboard
                CALL PROW(IBUF,I,1,NCOLS,IARRAY)
500             CONTINUE

                CALL PICOUT(IBUF,ONAME,0)
                CALL RELB(IBUF1)
                CALL RELB(IBUF2)
                CALL RELB(IBUF)
                CALL RESET
                STOP "<7><7><7>ADV"
                END
```

```
C******************************************************************
C                                                                 *
C     ADC.FR - DG FORTRAN 5 - LT MURAT CINCIOGLU AUG 1986         *
C                                                                 *
C       This program adds two complex image to obtain the         *
C       output file.                                              *
C                                                                 *
C       RELOAD LINE:                                              *
C         RLDR VCM @FLIB@                                         *
C                                                                 *
C       COMMAND LINE:                                             *
C         ADC                                                     *
C       Program will ask for input and output file name, create the  *
C         output file and then ask for file size.                *
C                                                                 *
C******************************************************************

      COMPLEX IN1(1024),IN2(1024),OUT(1024)
      INTEGER INFLNM1(7),INFLNM2(7),OFLNM1(7)
C
C ACCEPT INPUT
C
      ACCEPT"ENTER INPUT FILENAME #1 ->"
      READ(11,1)INFLNM1(1)
      ACCEPT"ENTER INPUT FILENAME #2 ->"
      READ(11,1)INFLNM2(1)
    1 FORMAT(S13)
      ACCEPT"ENTER OUTPUT FILENAME ->"
      READ(11,1)OFLNM1(1)

      CALL OPEN(1,INFLNM1,1,IER)
      CALL CHECK(IER)
      CALL OPEN(2,INFLNM2,1,IER)
      CALL CHECK(IER)

      CALL DFILW (OFLNM1,IER)
      CALL CFILW (OFLNM1,2,KER)
      CALL CHECK(KER)
      OPEN 3, OFLNM1,ATT="OR",ERR=100

100   CONTINUE
5     TYPE" "
      TYPE"ENTER SIZE OF FILES:"
      ACCEPT" 256, 128, 64, OR 32 -->",ISIZE
```

```
C
C   TEST FOR ONLY THE ALLOWABLE SIZES
C
      IF(ISIZE.EQ.256) GO TO 6
      IF(ISIZE.EQ.128) GO TO 6
      IF(ISIZE.EQ.64) GO TO 6
      IF(ISIZE.EQ.32) GO TO 6
      GO TO 5
6     CONTINUE    ; size is okay

      IFACTOR=256/ISIZE                        ;compute scaling factor
      ITIMES=64/IFACTOR**2-1

      DO 3 I=0,ITIMES

        CALL RDBLK(1,16*I,IN1,16,IER)
        CALL CHECK(IER)
        CALL RDBLK(2,16*I,IN2,16,IER)
        CALL CHECK(IER)

        DO 2 J=1,1024
          OUT(J)=IN1(J)+IN2(J)
2       CONTINUE

        CALL WRBLK(3,16*I,OUT,16,IER)
        CALL CHECK(IER)

3 CONTINUE

  CALL RESET
  STOP"<7><7><7>ADC"
  END
```

```fortran
C***********************************************************************
C                                                                     *
C         STAT.FR --- DG FORTRAN 5 - LT MURAT CINCIOGLU,  AUG 1986     *
C                                                                     *
C              This program obtains  the mean, variance,  mean square, *
C         maximum, and minumum values of a picture or a given region   *
C         in the picture.                                              *
C         RELOAD LINE:                                                 *
C                                                                     *
C              RLDR STAT  F5PICBUF.LB @FLIB@                            *
C                                                                     *
C         COMMAND LINE:                                                *
C                                                                     *
C              STAT                                                    *
C              Program will ask for the picture file name and          *
C         the coordinates(row, col) of the region where the mean,      *
C         variance,  mean square to be calculated.                     *
C                                                                     *
C                                                                     *
C***********************************************************************




         REAL MEAN, MEANSQ, VAR, STDEV, PR, SN, L(16), SV, N
         INTEGER K, V, Y, M, MIN, MAX
         PARAMETER NBUFSZ=300,  KTTYOUT=10,  KTTYIN=11
         PARAMETER NCOLSMAX=256
         INTEGER IBUF(NBUFSZ)
         INTEGER INAME(20)




C        INITIALIZE INPUT BUFFER AND READ IN PICTURE FILE


  10     WRITE(KTTYOUT, 996)
  996    FORMAT("ENTER INPUT PICTURE FILE NAME =", Z)
         READ(KTTYIN, 997) INAME(1)
  997    FORMAT(S39)

         CALL PICFMT(IBUF, INAME, IFLG)
         CALL GFMT(IBUF, NROWS, NCOLS, NBITS, IMODE)
         IF(IMODE.EQ.3) GO TO 10
         IF((NROWS.LT.3) .OR. (NCOLS.LT.3)) GO TO 10
         IF(NCOLS.GT.NCOLSMAX) GO TO 10
         IF(NBITS.GT.11) GO TO 10
         CALL MAKB(IBUF)
         CALL PICIN(IBUF, INAME, IFLG)


         TYPE" ENTER REGION BOUNDARIES"

         ACCEPT"ROW BOUNDARY    FROM-->", K
         ACCEPT"                TO  -->", M
         ACCEPT"COLUMN BOUNDARY FROM-->", V
```

```
        ACCEPT"                    TO  -->",Y

    MAX=0. 0
    MIN=15. 0
    N=0. 0
    DO 2 I=0, 15      ; initialize.
        L(I)=0. 0
2       CONTINUE



    DO 20 I=K, M               ; count possible intensity levels.
        DO 78 J=V, Y
            CALL GPNT(IBUF, I, J, IVAL)

            IF(IVAL. LT. MIN) MIN=IVAL        ; max, min search.
            IF(IVAL. GT. MAX) MAX=IVAL

            IF(IVAL. EQ. 0) L(0)=L(0)+1. 0
            IF(IVAL. EQ. 1) L(1)=L(1)+1. 0
            IF(IVAL. EQ. 2) L(2)=L(2)+1. 0
            IF(IVAL. EQ. 3) L(3)=L(3)+1. 0
            IF(IVAL. EQ. 4) L(4)=L(4)+1. 0
            IF(IVAL. EQ. 5) L(5)=L(5)+1. 0
            IF(IVAL. EQ. 6) L(6)=L(6)+1. 0
            IF(IVAL. EQ. 7) L(7)=L(7)+1. 0
            IF(IVAL. EQ. 8) L(8)=L(8)+1. 0
            IF(IVAL. EQ. 9) L(9)=L(9)+1. 0
            IF(IVAL. EQ. 10) L(10)=L(10)+1. 0
            IF(IVAL. EQ. 11) L(11)=L(11)+1. 0
            IF(IVAL. EQ. 12) L(12)=L(12)+1. 0
            IF(IVAL. EQ. 13) L(13)=L(13)+1. 0
            IF(IVAL. EQ. 14) L(14)=L(14)+1. 0
            IF(IVAL. EQ. 15) L(15)=L(15)+1. 0
            N=N+1 0            ; number of elements
78      CONTINUE

20      CONTINUE

    MEAN=0. 0
    VAR=0. 0
    MEANSQ=0. 0

    DO 88 I=0. 0, 15. 0
        PR =L(I)/N
        MEAN= MEAN+ I*PR
        VAR= VAR+( (I-MEAN)**2 )*PR
        MEANSQ=MEANSQ+ ( I**2 )*PR
88      CONTINUE
```

```
      STDEV=VAR**0.5
      SN=VAR/MEANSQ

C     REPORT MEAN, MEAN SQUARE, VARIANCE, MAX.,MIN.
      TYPE" "

      TYPE"MEAN =",MEAN
      TYPE" "
      TYPE"VARIANCE =",VAR




      TYPE" "
      TYPE"STANDART DEVIATION=",STDEV
      TYPE" "
      TYPE"MEANSQUARE =",MEANSQ
      TYPE" "
      TYPE"(VARIANCE)/(MEANSQUARE)=",SN
      TYPE" "
      TYPE"MINIMUM=",MIN
      TYPE"MAXIMUM=",MAX

      STOP"<7><7><7>STAT.FR"
      END
```

```
C*****************************************************************
C                                                                *
C         IMAGE.FR -- DG FORTRAN 5 - LT MURAT CINCIOGLU, AUG 1986 *
C                                                                *
C           This program is used to create the test image (Picture 1) *
C                                                                *
C       RELOAD LINE:                                             *
C                                                                *
C           RLDR IMAGE LINE CIRCLE F5PICBUF.LB @FLIB@            *
C                                                                *
C       COMMAND LINE:                                            *
C                                                                *
C           IMAGE                                                *
C           Program will ask for the output file name and the    *
C       background intensity level.                              *
C                                                                *
C                                                                *
C*****************************************************************


            PARAMETER KTTYIN=11,KTTYOUT=10,NBUFSZ=300
            INTEGER IBUF(NBUFSZ), IARRAY(256)
            INTEGER X1,X2,Y1,Y2,INAME(7),IBGL,IVAL
C
C           CALLS SUBROUTINE LINE(IBUF,IVAL,X1,Y1,X2,Y2)
C           CALLS SUBROUTINE CIRCLE(IBUF,IVAL,X,Y,RADIOUS)
C
C           X1<X2,  Y1<Y2


            write(KTTYOUT,12)
12          format("ENTER FILE NAME......>",Z)
            read(KTTYIN,14) INAME(1)
14          format( S39 )

            type"The background and image levels should be an integer,"
            type"between 0 and 15 ....."

            accept"ENTER BACKGROUND LEVEL ........>",IBGL
            accept"ENTER IMAGE LEVEL      ........>",IVAL
            type" "
            type"----------- program running ---------"

C           CREATE BUFFER
            call pfmt(IBUF,256,256,4,1)
            call makb(IBUF)

C           FILL BUFFER WITH BACKGROUND
            do 20 i= 1,256
               IARRAY(i)= IBGL ,
20          continue
            do 30 i= 1,256
               call prow(IBUF,i,1,256,IARRAY)
30          continue
```

```
C              PRIMITIVES TO CREATE THE IMAGE

       call CIRCLE(IBUF, IVAL, 0, 0, 10)

       call CIRCLE(IBUF, IVAL, 0, 0, 20)

       call CIRCLE(IBUF, IVAL, 0, 0, 25)
       call CIRCLE(IBUF, IVAL, 0, 0, 26)
       call CIRCLE(IBUF, IVAL, 0, 0, 27)

       call LINE(IBUF, IVAL, -110, 110, 110, 110)
       call LINE(IBUF, IVAL, -105, 105, 105, 105)
       call LINE(IBUF, IVAL, -100, 100, 100, 100)

       call LINE(IBUF, IVAL, -110, -110, 110, -110)
       call LINE(IBUF, IVAL, -105, -105, 105, -105)
       call LINE(IBUF, IVAL, -100, -100, 100, -100)
C
       call LINE(IBUF, IVAL, 110, -110, 110, 110)
       call LINE(IBUF, IVAL, 105, -105, 105, 105)
       call LINE(IBUF, IVAL, 100, -100, 100, 100)

       call LINE(IBUF, IVAL, -110, -110, -110, 110)
       call LINE(IBUF, IVAL, -105, -105, -105, 105)
       call LINE(IBUF, IVAL, -100, -100, -100, 100)

       call LINE(IBUF, IVAL, -89, 86, 89, 86)
       call LINE(IBUF, IVAL, -86, 83, 86, 83)
       call LINE(IBUF, IVAL, -83, 80, 83, 80)

       call LINE(IBUF, IVAL, -89, -86, 89, -86)
       call LINE(IBUF, IVAL, -86, -83, 86, -83)
       call LINE(IBUF, IVAL, -83, -80, 83, -80)


       call LINE(IBUF, IVAL, 84, -71, 84, 71)
       call LINE(IBUF, IVAL, 87, -74, 87, 74)
       call LINE(IBUF, IVAL, 90, -77, 90, 77)

       call LINE(IBUF, IVAL, -84, -71, -84, 71)
       call LINE(IBUF, IVAL, -87, -74, -87, 74)
       call LINE(IBUF, IVAL, -90, -77, -90, 77)

       call LINE(IBUF, IVAL, -50, 50, 50, 50)
       call LINE(IBUF, IVAL, 50, -50, 50, 50)
       call LINE(IBUF, IVAL, -50, -50, 50, -50)
       call LINE(IBUF, IVAL, -50, -50, -50, 50)
       call LINE(IBUF, IVAL, -50, 50, 50, -50)
       call LINE(IBUF, IVAL, -50, -50, 50, 50)

       call picout(IBUF, INAME, 1)
       call relb(IBUF)
       stop"<7><7><7>image.fr"
       end
```

```fortran
C                       This subroutine is used to draw circles in the
C                       spatial domain ( Ref. Chapter 4 ).

                        subroutine circle(IBUF,IVAL,X1,Y1,IR)
                        integer IBUF(300), IVAL, X1, Y1, IR
                        integer X, Y, D, IROW, ICOL

                        X= 0
                        Y= IR
                        D= 3 - 2*IR

10                          ICOL= (X+X1) + 128
                            IROW=(-1)*(Y+Y1)+128

                        call ppnt(IBUF,IROW,ICOL,IVAL)
                        ICOL=(Y+X1)+128
                        IROW=(-1)*(X+Y1)+128
                        call ppnt(IBUF,IROW,ICOL,IVAL)
                        ICOL=(Y+Y1)+128
                        IROW=(-1)*(-X+Y1)+128
                        call ppnt(IBUF,IROW,ICOL,IVAL)
                        ICOL=(X+X1)+128
                        IROW=(-1)*(-Y+Y1)+128
                        call ppnt(IBUF,IROW,ICOL,IVAL)
                        ICOL=(-X+X1)+128
                        IROW=(-1)*(-Y+Y1)+128
                        call ppnt(IBUF,IROW,ICOL,IVAL)
                        ICOL=(-Y+X1)+128
                        IROW=(-1)*(-X+Y1)+128
                        call ppnt(IBUF,IROW,ICOL,IVAL)
                        ICOL=(-Y+X1)+128
                        IROW=(-1)*(X+Y1)+128
                        call ppnt(IBUF,IROW,ICOL,IVAL)
                        ICOL=(-X+X1)+128
                        IROW=(-1)*(Y+Y1) +128
                        call ppnt(IBUF,IROW,ICOL,IVAL)
                        if(X.eq.Y) call ppnt(IBUF,IROW,ICOL,IVAL)
                        if (X.ge.Y) go to 15

                            if (D.ge.0) go to 12
                               D=  D + 4*X + 6
                               X= X+1
                            go to 10

12                             D= D+ (X-Y) + 10
                               Y=Y-1
                               X=X+1
                               go to 10
15                      return
                        end
```

```
C                    This Subroutine is used to draw line in the
C                    spatial domain (ref. Chapter 4)


                     subroutine LINE(ibuf,ival,x1,y1,x2,y2)
                     integer ibuf,ival,x1,y1,x2,y2
                     integer lx,ly,incr1,incr2,sx,sy,ld,xend
                     integer intx,inty,dm
                     real dx,dy,x,y,m
                     if(x1.eq.x2) go to 300


                     dy=y2-y1
                     dx=x2-x1
                     m=dy/dx
                     if( m.lt.0) go to 150
                     lx=x2-x1
                     ly=y2-y1
                     if(lx.lt.0) lx=(-1)*lx
                     if(ly.lt.0) ly=(-1)*ly
                     ld=2*ly-lx
                     incr1=2*ly
                     incr2=2*(ly-lx)

                     if (x1.lt.x2) go to 25
                     sx=x2
                     sy=y2
                     xend=x1
                     go to 30
      25             sx=x1
                     sy=y1
                     xend=x2
      30             irow=(-1)*sy+128
                     icol=sx+128
                     call ppnt(ibuf,irow,icol,ival)

      35             if (sx.ge.xend) go to 50
                     sx=sx+1
                     if(ld.ge.0) go to 40
                     ld=ld+incr1
                     go to 45
      40             sy=sy+1
                     ld=ld+incr2
      45             irow=(-1)*sy+128
                     icol=sx+128
                     call ppnt(ibuf,irow,icol,ival)
                     go to 35
```

```
150                if(dx.lt.dy) go to 500
                   b=y1-m*x1
                   do 160 i=x1,x2
                      x=i
                      y=m*x+b
                      inty=y
                      intx=x
                      irow=(-1)*inty +128
                      icol= intx+128
                      call ppnt(ibuf,irow,icol,ival)

160                continue
                   go to 50
500                x=x1
                   do 200 i=y1,y2
                      intx=x
                      irow=(-1)*i + 128
                      icol=intx+ 128
                      call ppnt(ibuf,irow,icol,ival)
                      x=x+(1/m)
200                continue
                   go to 50
300                if( y1.lt.y2) go to 350
                   dm=y1
                   y1=y2
                   y2=dm
350                do 250 i=y1,y2
                      irow=(-1)*i + 128
                      icol= x1 + 128
                      call ppnt(ibuf,irow,icol,ival)
250                continue
50                 return
                   end
```

```
C                      This subroutine creates a subimage from an image
C                      INAME : input file name
C                      IOUTNAME : output file
C                      ISIZE : output file size
C                      C,R : starting column and row  in the input image

                       SUBROUTINE SUBIMG(INAME, IOUTNM, ISIZE, C, R)

                       PARAMETER NBUFSZ=300
                       PARAMETER NCOLSMAX=256
                       INTEGER IBUF2(NBUFSZ), IBUF(NBUFSZ)
                       INTEGER IARRAY(NCOLSMAX)
                       INTEGER C,R

C                      PICBUF FOR INPUT FILE
                       CALL PICFMT(IBUF, INAME, IHDR)
                       CALL GFMT(IBUF, NROWS, NCOLS, NBITS, IMODE)
                       CALL MAKB(IBUF)
                       CALL PICIN(IBUF, INAME, IHDR)


C                      DELETE OUTPUT FILE IF IT EXISTS
                       CALL DFILW(IOUTNM, IER)
                       CALL CHECK(IER)
                       IF(IER.NE.1) GO TO 15
15                     CONTINUE
                       IFACTOR=256/ISIZE
C
C                      PICBUF FOR OUTPUT FILE
                       CALL GFMT(IBUF, NROWS, NCOLS, NBITS, IMODE)
                       NROWS2=NROWS/IFACTOR
                       NCOLS2=NCOLS/IFACTOR
                       CALL PFMT(IBUF2, NROWS2, NCOLS2, NBITS, IMODE)
                       CALL MAKB(IBUF2)

                       ISTART=R
                       ISTOP=R+ISIZE-1
                       ICOL=C
                       IROW2=1
                       ICOL2=1
C
                       DO 10 IROW=ISTART, ISTOP
                       CALL GROW(IBUF, IROW, ICOL, ISIZE, IARRAY)
                       CALL PROW(IBUF2, IROW2, ICOL2, ISIZE, IARRAY)
                       IROW2=IROW2+1
10                     CONTINUE
C
C
                       CALL PICOUT(IBUF2, IOUTNM, IHDR)
                       CALL RELB(IBUF2)
                       CALL RELB(IBUF)
                       RETURN
                       END
```

```fortran
C           This subroutine converts an integer file
C           to a complex form.

C           ISIZE : size of the files
C           INNAME: integer file name
C           OUTNAME : complex (output) file name


            SUBROUTINE SVTC(ISIZE, INNAME, OUTNAME)
            INTEGER TMP(256), IN(1024)
            INTEGER INNAME(7), OUTNAME(7)
            COMPLEX OUT(1024)

            CALL OPEN(8, INNAME, 1, IER)
            CALL CHECK(IER)
C           CALL DFILW(OUTNAME, IER)
C           CALL CFILW(OUTNAME, 2, KER)
C           CALL CHECK(KER)
            CALL OPEN(9, OUTNAME, 2, IER)
            CALL CHECK(IER)

C           OPEN 9, OUTNAME, ATT="OR", ERR=100
C           CONTINUE
            IFACTOR=256/ISIZE
            ITIMES=64/IFACTOR**2-1

            DO 30 I=0, ITIMES
            CALL RDBLK(8, I, TMP, 1, IER)
            CALL CHECK(IER)
            CALL UNP(256, TMP, IN)
            DO 40 J=1, 1024
                    OUT(J)=CMPLX(FLOAT(IN(J)), 0.0)
40          CONTINUE
            CALL WRBLK(9, 16*I, OUT, 16, IER)
            CALL CHECK(IER)
30          CONTINUE
            CALL RESET
            RETURN
            END
```

```fortran
C            (Ref. KING, D.A., INHOUSE ARCHIVE    )
C            (AFIT- Digital Signal Processing Lab.)
C
C            OPTIONS :
C                     1  : Forward transform (Origin at CENTER)
C                     2  : Inverse transform (Origin at CENTER)
C                     3  : Forward transform (Origin at CORNER)
C                     4  : Inverse transform (Origin at CORNER)
C                     5  : Transform 2D complex file


             SUBROUTINE SFFT2(INAME, OPTION)

             COMPLEX X(512), Y(512)
             INTEGER OPTION

             ICHAN=1
             CALL OPEN(ICHAN, INAME, 2, IER)
             IF(IER.EQ.1) GO TO 30
             TYPE"in SFFT2. error-openinin file", IER
             CALL CLOSE(ICHAN, IER)
             GO TO 99
C
C            COMPUTE 2D-FFT
C
30           IOPT=OPTION
             CALL FFT2(ICHAN, X, Y, IOPT, IER)
             IF(IER.EQ.1) TYPE"NORMAL COMPLETION"
             IF(IER.EQ.4) TYPE"INVALID FILE SIZE"
99           RETURN
             END




C            This subroutine will unpack four 4-bit integers
C            from a 16-bit integer word  The pixels in a video file
C            have to be unpacked if each pixel is to be operated on
C            separately ( ref 29 )

             SUBROUTINE UNP(N, PIXWORD, PIXELS)
             INTEGER PIXWORD(N), PIXELS(4, N)    , four pixels per word
             DO 1 I=1, N                         , 'N' allows higher order
                                                 , arrays to be passed
             DO 1 J=1, 4
             PIXELS((5-J), I)=15 AND PIXWORD(I) , pick off right pixel
1            PIXWORD(I)=ISHFT(PIXWORD(I), -4) , shift word 4 bits right
             IF(MOD(N, 12) EQ 0) TYPE"UNP DONE ", N , to pick off next pixel
             RETURN
             END
```

Bibliography

1. Aboutalib, A. O., and Silverman, L. M., <u>Restoration of Motion Degraded Images</u>, Andrews, H.E., <u>Tutorial Selected Papers in Digital Image Processing</u>, IEEE Computer Society, 1978.

2. Andrews, H. C., and Morton , J. B., "A Posteriror; Method of Image Restoration", <u>Journal of the Optical Society of America</u>, Volume 69, No. 2., February 1979, pp. 280-290.

3. Cannon, M., "Blind Deconvolution of Spatially Invariant Image Blurs with Phase", <u>IEEE Transactions on Acoustic, Speech, and Signal Processing</u>, Volume ASSP-24, NO. 1, February 1976, pp. 58-63.

4. Cannon, T. M., Trussel, H. J., and Hunt, B. R., "Comparison of Image Restoration Methods", <u>Applied Optics</u>, Volume 17, 1978, pp. 3384-3390.

5. Chu, N. Y., and McGilliam, C. D., "Image Restoration Filters Based on a 1-0 Weighting Over the Domain of Support of the PSF", <u>IEEE Transactions on Acoustic, Speech, and Signal Processing</u>, Volume ASSP-27, 1979, pp. 457-464.

6. Fogiel, M., <u>Handbook of Mathematical Formulas, Tables, Functions, Graphs, Transforms</u>, Research and Education Association, New York, 1983.

7. Gennery, Donald B., "Determination of Optical Transfer Function by Inspection of Frequency Domain Plot", <u>Journal of the Optical Society of America</u>, Volume 63, No. 12, December 1973, pp. 1571-1577.

8. Gonzolez, A. C., and Wintz, P., <u>Digital Image Processing</u>, Addison-Wesley, Massachusetts, 1977.

9. Goodman, J. W., <u>Introduction to Fourier Optics</u>, MacGraw-Hill, New York, 1968.

10. Helstrom, C. W., "Image Restoration by the Method of Least Squares", <u>Journal of the Optical Society of America</u>, Volume 57, No. 3, March 1967, pp. 297-303.

11. Huang T. S., Schreiber, W. F., and Tretiak, O. J., "Image Processing", *Proceedings of the IEEE*, Volume 58, No. 11, November 1971, pp. 1586-1609.

12. Hunt, B. R., "Deconvolution of Linear Systems by Constrained Regression and its Relationship to the Wiener Theory", *IEEE Trans. Automat. Cont.*, AC-17, 1972, pp. 703-705.

13. Hunt, B. R., "The Application of Constraint Least Squares Estimation to Image Restoration by Digital Computer", *IEEE Trans Comput.* C-22, 1973, pp. 703-705.

14. Jain, A. K., "A Semicausal Model for Recorsive Filtering of two-dimensional Images", Andrews, H. C., *Tutorial Selected Papers in Image Processing*, IEEE Computer Society, 1978.

15. King, David A., "Programmers Guide to PICBUF: A Virtual Memory System for Digital Picture Processing", *Signal Processing Laboratory*, Air Force Institute of Technology, Wright-Patterson AFB, Ohio, August 1984.

16. Naderi, F. and Sawchuk, A. A., "Estimation of Images Degraded by Film-Grain Noise", Chellappa, R. and Sawchuk, A. A., *Digital Image Processing and Analysis: Volume 1, Digital Image Processing*, IEEE Computer Society, 1985.

17. Nahi, N. E., "Bayesian Recursive Image Estimation", Andrews, H. C., *Tutorial Selected Papers in Digital Image Processing*, IEEE Computer Society, 1978.

18. Potmesil, M., and Chakravarty, I., "Modelling Motion Blur in Computer Generated Image", *Computer Graphics*, Vol. 17, No. 3, 1983, pp. 389-399.

19. Pratt, W. K., *Digital Image Processing*, John Wiley & Sons, New York, 1978.

20. Rosenfeld, A., and Kak, Avinash C., *Digital Picture Processing*, Academic Press, New York, 1982.

21. Sondhi, M. M., "Image Restoration: The Removal of Spatially Invariant Degradations". *Proceedings of the IEEE*, Vol. 60, No. 7, July 1972.

81

22. Stockham G., Cannon, T. M., and Ingebretsen, R. B.,
"Blind Deconvolution Through Digital Signal Processing",
Proceedings of the IEEE, Volume 63, No. 4, April 1975,
pp. 678-692.

23. Stokseth, Per A., "Properties of the Defocused Optical System"
Journal of the Optical Society of America, Volume 59, NO. 10,
October 1969, pp. 1314-1321.

24. Tao, M. K., and Weinhaus, F. M., "Adaptive Noise Cancelling
Applied to Image Restoration". IEEE International Conference
on Acoustics, Speech, and Signal Processing, Volume 2, March
1985, pp. 684-687.

25. Urkowitz, H., Signal Theory and Random Processes, Artech
House Inc., Dedham, Massachusetts, 1983.

26. Widrow, B., et. al., "Adaptive Noise Cancelling: Principles
and Applications", Proceedings of the IEEE, Volume 63,
December, 1975, pp. 1692-1716.

27. Widrow, B., Stearns, S. D., Adaptive Signal Processing,
Prentice-Hall Inc., Englewood Cliffs, New Jersey, 1985.

<u>Vita</u>

First Lieutenant Murat Cincioglu was born on 10 August 1961, in Sungurlu, Corum, Turkey. He graduated from Sungurlu High School in Sungurlu in 1978, and attended Turkish Air Force Academy graduating in 1982 as a distinguished graduate with a Bachelor of Science in Electrical Engineering. He was then assigned to Turkish Armed Forces Staff Academy, Istanbul as a project officer on electronic communications systems until entering the School of Engineering, the United States Air Force Institute of Technology to work on his master's degree in Communications and RADAR in 1984.

Permanent Address:

Egitim Daire Baskanligi
Dis Kurslar Subesi
Bakanliklar/ANKARA-TURKEY

REPORT DOCUMENTATION PAGE

1a. REPORT SECURITY CLASSIFICATION	1b. RESTRICTIVE MARKINGS
UNCLASSIFIED	

2a. SECURITY CLASSIFICATION AUTHORITY	3. DISTRIBUTION/AVAILABILITY OF REPORT
2b. DECLASSIFICATION/DOWNGRADING SCHEDULE	Approved for Public Release Distribution Unlimited

4. PERFORMING ORGANIZATION REPORT NUMBER(S)	5. MONITORING ORGANIZATION REPORT NUMBER(S)
AFIT/GE/ENG/86S-1	

6a. NAME OF PERFORMING ORGANIZATION	6b. OFFICE SYMBOL (If applicable)	7a. NAME OF MONITORING ORGANIZATION
School of Engineering	AFIT/ENG	

6c. ADDRESS (City, State and ZIP Code)	7b. ADDRESS (City, State and ZIP Code)

8a. NAME OF FUNDING/SPONSORING ORGANIZATION	8b. OFFICE SYMBOL (If applicable)	9. PROCUREMENT INSTRUMENT IDENTIFICATION NUMBER
Foreign Technology Division	FTD/SONA	

8c. ADDRESS (City, State and ZIP Code)	10 SOURCE OF FUNDING NOS

	PROGRAM ELEMENT NO	PROJECT NO	TASK NO	WORK UNIT NO

11. TITLE (Include Security Classification)
See Box 19

12. PERSONAL AUTHOR(S)
Gümüşgül, Murat

13a. TYPE OF REPORT	13b. TIME COVERED	14. DATE OF REPORT (Yr. Mo. Day)	15. PAGE COUNT
MS Thesis	FROM Apr 85 TO Sep 86	1986 September	183

16. SUPPLEMENTARY NOTATION

17	COSATI CODES		18 SUBJECT TERMS (Continue on reverse if necessary and identify by block number)
FIELD	GROUP	SUB GR	Parameter Estimation, Image Restoration,
14	05		Point Spread Function, Noise-to-Signal Ratio

19. ABSTRACT (Continue on reverse if necessary and identify by block number)

Title: Parameter Estimation for the Blind Restoration
         of Blurred Imagery

Thesis Chairman: David A. King, Major, USAF
                   Instructor of Electrical Engineering

Approved for public release: IAW AFR 190-1?

20. DISTRIBUTION/AVAILABILITY OF ABSTRACT	21. ABSTRACT SECURITY CLASSIFICATION
UNCLASSIFIED/UNLIMITED ☒ SAME AS RPT ☐ DTIC USERS ☐	Unclassified

22a. NAME OF RESPONSIBLE INDIVIDUAL	22b. TELEPHONE NUMBER (Include Area Code)	22c. OFFICE SYMBOL
David A. King, Major, USAF	513-255-3576	AFIT-ENG

DD FORM 1473, 83 APR   EDITION OF 1 JAN 73 IS OBSOLETE   Unclassified

Abstract

Methods to estimate the optical transfer function (OTF) of the degradation and the noise-to-signal ratio in a degraded image are presented which use no prior information about the degradation and the noise. Two types of degradations are considered: uniform linear camera motion and out-of-focus camera with circular aperture. The OTF of the out-of-focus camera is estimated by inspection of the spectra of the degraded image and from average over the spectra of subsections of the degraded image. A line estimation method is described to estimate the degrading OTF of the linear camera motion in one direction. An additional method called the "logarithmic estimate" is also developed. Frequency and space domain estimation methods are developed for the noise-to-signal ratio for the case of additive gaussian noise. Inverse, Wiener, and power spectrum equalization filters based on these estimates are implemented on a digital computer to restore a variety of degraded images and examples of blind restoration of these degraded images are presented.

END

4-87

DTIC